



## Product Change Notification / SYST-29ULYA009

---

### Date:

11-May-2022

### Product Category:

8-bit Microcontrollers

### PCN Type:

Document Change

### Notification Subject:

ERRATA - PIC18(L)F26/45/46/55/56K42 Silicon Errata and Data Sheet Clarification

### Affected CPNs:

[SYST-29ULYA009\\_Affected\\_CPN\\_05112022.pdf](#)

[SYST-29ULYA009\\_Affected\\_CPN\\_05112022.csv](#)

### Notification Text:

SYST-29ULYA009

Microchip has released a new Product Documents for the PIC18(L)F26/45/46/55/56K42 Silicon Errata and Data Sheet Clarification of devices. If you are using one of these devices please read the document located at [PIC18\(L\)F26/45/46/55/56K42 Silicon Errata and Data Sheet Clarification](#).

**Notification Status:** Final

#### Description of Change:

- Added Module 9.4 Double Sample Conversions, 13 Central Processing Unit (CPU), and 13.1 FSR Shadow Registers.

**Impacts to Data Sheet:** None

**Reason for Change:** To Improve Productivity

**Change Implementation Status:** Complete

**Date Document Changes Effective:** 11 May 2022

**NOTE:** Please be advised that this is a change to the document only the product has not been changed.

Markings to Distinguish Revised from Unrevised Devices: N/A

## Attachments:

[PIC18\(L\)F26/45/46/55/56K42 Silicon Errata and Data Sheet Clarification](#)

Please contact your local [Microchip sales office](#) with questions or concerns regarding this notification.

## Terms and Conditions:

If you wish to receive Microchip PCNs via email please register for our PCN email service at our [PCN home page](#) select register then fill in the required fields. You will find instructions about registering for Microchips PCN email service in the [PCN FAQ](#) section.

If you wish to change your PCN profile, including opt out, please go to the [PCN home page](#) select login and sign into your myMicrochip account. Select a profile option from the left navigation bar and make the applicable selections.

Affected Catalog Part Numbers (CPN)

PIC18F26Q10-E/SSVAO  
PIC18F26Q10-E/SO  
PIC18F26Q10-E/SOVAO  
PIC18F45Q10-E/MP  
PIC18F46Q10-E/MP  
PIC18F46Q10-E/MPVAO  
PIC18F452-E/P  
PIC18F452-E/L  
PIC18F452-E/ML  
PIC18F452-E/PT  
PIC18F452-E/PTC34  
PIC18LF452-I/P  
PIC18F452-I/P  
PIC18F4539-I/P  
PIC18LF4539-I/P  
PIC18F452-I/PREL  
PIC18LF452-I/L  
PIC18F452-I/L  
PIC18F452-I/LVAO  
PIC18LF452-I/ML  
PIC18F452-I/ML  
PIC18LF452-I/PT  
PIC18F452-I/PT  
PIC18F452-I/PTC17  
PIC18F452-I/PTVAO  
PIC18F452T-I/L  
PIC18LF452T-I/ML  
PIC18LF452T-I/PT  
PIC18F452T-I/PT  
PIC18F452T-I/PTVAO  
PIC18F458-E/P  
PIC18F458-E/L  
PIC18F458-E/PT  
PIC18LF458-I/P  
PIC18F458-I/P  
PIC18F458-I/PREL  
PIC18LF458-I/L  
PIC18F458-I/L  
PIC18LF458-I/PT  
PIC18F458-I/PT  
PIC18F458T-I/L  
PIC18F458T-I/PT  
PIC18F458T-I/PTVAO  
PIC18F458T-E/PTVAO  
PIC18LF452-I/PTC33  
PIC18F2620-E/SP

PIC18F2620-E/SO  
PIC18F4620-E/P  
PIC18F4620-E/ML  
PIC18F4620-E/PT  
PIC18LF2620-I/SP  
PIC18F2620-I/SP  
PIC18F2620-I/SPC03  
PIC18F2620-I/SPREL  
PIC18F2620-I/SOB4  
PIC18LF2620-I/SO  
PIC18F2620-I/SO  
PIC18LF4620-I/P  
PIC18F4620-I/P  
PIC18F4620-I/PREL  
PIC18LF4620-I/ML035  
PIC18LF4620-I/ML  
PIC18F4620-I/ML  
PIC18LF4620-I/PT  
PIC18F4620-I/PT  
PIC18LF4620-I/PTVAO  
PIC18LF2620T-I/SO  
PIC18F2620T-I/SO  
PIC18LF2620T-I/SOV03  
PIC18F2620T-I/SOV04  
PIC18F2620T-I/SOV05  
PIC18LF4620T-I/ML035  
PIC18LF4620T-I/ML  
PIC18F4620T-I/ML  
PIC18LF4620T-I/PT  
PIC18F4620T-I/PT  
PIC18LF4620T-I/PTVAO  
PIC18F4620T-E/PTV01  
PIC18F2610-I/SP  
PIC18F2610-I/SO  
PIC18LF4610-I/P  
PIC18F4610-I/P  
PIC18F4610-I/ML  
PIC18LF4610-I/PT  
PIC18F4610-I/PT  
PIC18F4525-E/P  
PIC18F4525-E/PT  
PIC18LF4525-I/P  
PIC18F4525-I/P  
PIC18LF4525-I/ML  
PIC18F4525-I/ML  
PIC18LF4525-I/PT  
PIC18F4525-I/PT  
PIC18LF4525T-I/ML  
PIC18LF4525T-I/PT

PIC18F4525T-I/PT  
PIC18LF4515-I/P  
PIC18F4515-I/P  
PIC18LF4515-I/ML  
PIC18F4515-I/ML  
PIC18LF4515-I/PT  
PIC18F4515-I/PT  
PIC18LF4550-I/P  
PIC18F4550-I/P  
PIC18LF4553-I/P  
PIC18F4553-I/P  
PIC18F4553-I/PREL  
PIC18LF4550-I/ML  
PIC18F4550-I/ML  
PIC18F4550-I/MLVAO  
PIC18LF4550-I/PT  
PIC18F4550-I/PT  
PIC18F4680T-I/PT045  
PIC18F4680T-I/PTGC01  
PIC18F4520-E/P  
PIC18F4523-E/P  
PIC18F4520-E/ML  
PIC18F4520-E/PT  
PIC18F4523-E/PT  
PIC18LF4520-I/P  
PIC18F4520-I/P  
PIC18LF4523-I/P  
PIC18F4523-I/P  
PIC18F4523-I/PREL  
PIC18LF4520-I/ML  
PIC18F4520-I/ML  
PIC18LF4523-I/ML  
PIC18F4523-I/ML  
PIC18F4520-I/PTB4  
PIC18LF4520-I/PT  
PIC18F4520-I/PT  
PIC18LF4523-I/PT  
PIC18F4523-I/PT  
PIC18F4520-I/PTC14  
PIC18LF4520T-I/ML  
PIC18F4520T-I/ML  
PIC18LF4520T-I/PT  
PIC18F4520T-I/PT  
PIC18LF4523T-I/PT  
PIC18F4523T-I/PT  
PIC18F4520T-E/ML  
PIC18F4520T-E/PT  
PIC18F4520T-E/PTV05  
PIC18F4510-E/P

PIC18F4510-I/P  
PIC18LF4510-I/ML  
PIC18LF4510-I/PT  
PIC18F4510-I/PT  
PIC18LF4510T-I/PT  
PIC18F2682-E/SP  
PIC18F2682-E/SO  
PIC18F2682-I/SP  
PIC18LF2682-I/SO  
PIC18F2682-I/SO  
PIC18F2682T-I/SOV01  
PIC18F2685-E/SP  
PIC18F2685-E/SO  
PIC18LF2685-I/SP  
PIC18F2685-I/SP  
PIC18F2685-I/SPREL  
PIC18LF2685-I/SO  
PIC18F2685-I/SO  
PIC18F2685-I/SOREL  
PIC18F2685T-I/SO  
PIC18F4682-E/ML  
PIC18F4682-E/PT  
PIC18LF4682-I/P  
PIC18F4682-I/P  
PIC18LF4682-I/ML  
PIC18F4682-I/ML  
PIC18LF4682-I/PT  
PIC18F4682-I/PT  
PIC18F4682T-I/PT020  
PIC18F4682T-I/PT021  
PIC18F4682T-I/PT022  
PIC18F4682T-I/PTVAO  
PIC18F4685-E/P  
PIC18F4685-E/ML  
PIC18F4685-E/PT025  
PIC18F4685-E/PT  
PIC18LF4685-I/P  
PIC18F4685-I/P  
PIC18F4685-I/PREL  
PIC18LF4685-I/ML  
PIC18F4685-I/ML  
PIC18LF4685-I/PT  
PIC18F4685-I/PT  
PIC18F4685T-I/ML  
PIC18F4685T-I/PT  
PIC18F4685T-E/PT025  
PIC18F4685T-E/PT027  
PIC18F4685T-E/PT028  
PIC18F4685T-E/PTV02

PIC18F2680-E/SP  
PIC18F2680-E/SO  
PIC18F4680-E/P  
PIC18F4680-E/ML  
PIC18F4680-E/MLV01  
PIC18F4680-E/PT  
PIC18F4680-E/PTC04  
PIC18F4680-E/PTVAO  
PIC18LF2680-I/SP  
PIC18F2680-I/SP  
PIC18F2680-I/SO061  
PIC18F2680-I/SO062  
PIC18F2680-I/SO067  
PIC18F2680-I/SO070  
PIC18F2680-I/SO071  
PIC18LF2680-I/SO  
PIC18F2680-I/SO  
PIC18F2680-I/SOVAO  
PIC18LF4680-I/P  
PIC18F4680-I/P  
PIC18LF4680-I/ML  
PIC18F4680-I/ML  
PIC18LF4680-I/PT  
PIC18F4680-I/PT  
PIC18F2680-H/SOVAO  
PIC18F2680T-H/SOVAO  
PIC18F4680T-H/PTVAO  
PIC18F2680-H/SP  
PIC18F2680-H/SO  
PIC18F4680-H/PT  
PIC18F4680-H/PTVAO  
PIC18F2680T-I/SO056  
PIC18F2680T-I/SO057  
PIC18F2680T-I/SO059  
PIC18F2680T-I/SO060  
PIC18F2680T-I/SO061  
PIC18F2680T-I/SO062  
PIC18F2680T-I/SO063  
PIC18F2680T-I/SO065  
PIC18F2680T-I/SO066  
PIC18F2680T-I/SO067  
PIC18F2680T-I/SO068  
PIC18F2680T-I/SO070  
PIC18F2680T-I/SO071  
PIC18LF2680T-I/SO  
PIC18F2680T-I/SO  
PIC18F2680T-I/SOV03  
PIC18F2680T-I/SOV06  
PIC18F2680T-I/SOVAO

PIC18F4680T-I/ML  
PIC18F4680T-I/PT033  
PIC18LF4680T-I/PT  
PIC18F4680T-I/PT  
PIC18F4680T-E/PT055  
PIC18F4680T-E/PT058  
PIC18F4680T-E/PT072  
PIC18F4680T-E/PT  
PIC18F4585-E/P  
PIC18F4585-E/ML  
PIC18F4585-E/PT  
PIC18LF4585-I/P  
PIC18F4585-I/P  
PIC18LF4585-I/ML  
PIC18F4585-I/ML  
PIC18LF4585-I/PT  
PIC18F4585-I/PT  
PIC18F4585-I/PTV03  
PIC18F4585-H/PTVAO  
PIC18F4585T-H/PTVAO  
PIC18F4585-H/ML  
PIC18F4585-H/PT  
PIC18F4585T-I/PT021  
PIC18LF4585T-I/PT  
PIC18F4585T-I/PT  
PIC18F4580-E/P  
PIC18F4580-E/ML  
PIC18F4580-E/PT  
PIC18LF4580-I/P  
PIC18F4580-I/P  
PIC18LF4580-I/ML  
PIC18F4580-I/ML  
PIC18F4580-I/MLVAO  
PIC18LF4580-I/PT  
PIC18F4580-I/PT  
PIC18F4580-I/PTC02  
PIC18F4580T-I/MLVAO  
PIC18LF4580T-I/PT  
PIC18F4580T-I/PT  
PIC18F4580T-I/PTC01  
PIC18F26Q10-E/SP  
PIC18F26Q10-E/ML  
PIC18F26Q10-E/MLVAO  
PIC18F26Q10-E/SS  
PIC18F45Q10-E/P  
PIC18F46Q10-E/P  
PIC18F26Q10-E/STX  
PIC18F45Q10-E/PT  
PIC18F46Q10-E/PT



PIC18F45Q10-E/PTVAO  
PIC18F26Q10-I/SP  
PIC18F26Q10-I/ML  
PIC18F26Q10-I/SSC01  
PIC18F26Q10-I/SS  
PIC18F26Q10-I/SSVAO  
PIC18F26Q10-I/SO  
PIC18F45Q10-I/MP  
PIC18F46Q10-I/MP  
PIC18F45Q10-I/P  
PIC18F46Q10-I/P  
PIC18F26Q10-I/STX  
PIC18F45Q10-I/PTC02  
PIC18F45Q10-I/PT  
PIC18F46Q10-I/PT  
PIC18F45Q10-I/PTVAO  
PIC18F46Q10-I/PTVAO  
PIC18F26Q10T-I/ML  
PIC18F26Q10T-I/SS020  
PIC18F26Q10T-I/SSC01  
PIC18F26Q10T-I/SS  
PIC18F26Q10T-I/SSV01  
PIC18F26Q10T-I/SSVAO  
PIC18F26Q10T-I/SO  
PIC18F45Q10T-I/MP  
PIC18F46Q10T-I/MP  
PIC18F26Q10T-I/STX  
PIC18F45Q10T-I/PTC02  
PIC18F45Q10T-I/PT  
PIC18F46Q10T-I/PT  
PIC18F45Q10T-I/PTVAO  
PIC18F46Q10T-I/PTVAO  
PIC18F26Q10T-E/MLVAO  
PIC18F45Q10T-E/MP  
PIC18F26Q43-E/ML  
PIC18F26Q43-E/SS  
PIC18F45Q43-E/MP  
PIC18F46Q43-E/ML  
PIC18F26Q43-I/SP  
PIC18F26Q43-I/ML  
PIC18F26Q43-I/SS  
PIC18F26Q43-I/SO  
PIC18F45Q43-I/MP  
PIC18F46Q43-I/MP  
PIC18F46Q43-I/P  
PIC18F26Q43-I/STX  
PIC18F46Q43-I/ML  
PIC18F45Q43-I/PT  
PIC18F46Q43-I/PT

PIC18F55Q43-I/PT  
PIC18F26Q43T-I/ML  
PIC18F26Q43T-I/SS  
PIC18F26Q43T-I/SO  
PIC18F45Q43T-I/MP  
PIC18F46Q43T-I/MP  
PIC18F26Q43T-I/STX  
PIC18F46Q43T-I/ML  
PIC18F46Q43T-I/PT  
PIC18F55Q43-E/6LX  
PIC18F45Q43-E/P  
PIC18F45Q43-E/ML  
PIC18F45Q43-E/PT  
PIC18F55Q43-E/PT  
PIC18F55Q43-I/6LX  
PIC18F45Q43-I/P  
PIC18F45Q43-I/ML  
PIC18F55Q43T-I/6LX  
PIC18F45Q43T-I/ML  
PIC18F45Q43T-I/PT  
PIC18F55Q43T-I/PT  
PIC18F26Q83-E/5N  
PIC18F26Q84-E/5N  
PIC18F26Q83-E/SP  
PIC18F26Q84-E/SP  
PIC18F26Q83-E/SS  
PIC18F26Q84-E/SS  
PIC18F26Q83-E/SO  
PIC18F26Q84-E/SO  
PIC18F46Q83-E/NHX  
PIC18F46Q84-E/NHX  
PIC18F46Q83-E/P  
PIC18F46Q84-E/P  
PIC18F46Q83-E/PT  
PIC18F46Q84-E/PT  
PIC18F26Q83-I/5N  
PIC18F26Q84-I/5N  
PIC18F26Q83-I/SP  
PIC18F26Q84-I/SP  
PIC18F26Q83-I/SS  
PIC18F26Q84-I/SS  
PIC18F26Q83-I/SO  
PIC18F26Q84-I/SO  
PIC18F46Q83-I/NHX  
PIC18F46Q84-I/NHX  
PIC18F46Q83-I/P  
PIC18F46Q84-I/P  
PIC18F46Q83-I/PT  
PIC18F46Q84-I/PT

PIC18F26Q83T-I/5N  
PIC18F26Q83T-E/5N  
PIC18F26Q84T-E/SS  
PIC18F26Q43-E/SP  
PIC18F26Q43-E/SO  
PIC18F46Q43-E/MP  
PIC18F46Q43-E/P  
PIC18F26Q43-E/STX  
PIC18F46Q43-E/PT  
PIC18LF46KS22T-I/MLV01  
PIC18F46K20/WMD03  
PIC18F46K20-E/P  
PIC18F46K20-E/MV  
PIC18F46K20-E/ML  
PIC18F46K20-E/PT  
PIC18F46K20-E/PTC03  
PIC18F46K20-I/P  
PIC18F46K20-I/MV  
PIC18F46K20-I/ML  
PIC18F46K20-I/MLV01  
PIC18F46K20-I/PT  
PIC18F46K20-I/PTC06  
PIC18F46K20T-I/ML  
PIC18F46K20T-I/MLV01  
PIC18F46K20T-I/MLVAO  
PIC18F46K20T-I/PT024  
PIC18F46K20T-I/PT025  
PIC18F46K20T-I/PT028  
PIC18F46K20T-I/PT030  
PIC18F46K20T-I/PT031  
PIC18F46K20T-I/PT  
PIC18F46K20T-E/ML  
PIC18F46K20T-E/PTC03  
PIC18F26K20-E/SP  
PIC18F26K20-E/ML  
PIC18F26K20-E/SS  
PIC18F26K20-E/SSC05  
PIC18F26K20-E/SO  
PIC18F26K20-I/SP  
PIC18F26K20-I/ML035  
PIC18F26K20-I/ML045  
PIC18F26K20-I/ML048  
PIC18F26K20-I/ML049  
PIC18F26K20-I/ML050  
PIC18F26K20-I/ML056  
PIC18F26K20-I/ML057  
PIC18F26K20-I/ML  
PIC18F26K20-I/MLC03  
PIC18F26K20-I/MLVAO

PIC18F26K20-I/SS  
PIC18F26K20-I/SSLPR  
PIC18F26K20-I/SO024  
PIC18F26K20-I/SO  
PIC18F26K20T-I/ML026  
PIC18F26K20T-I/ML029  
PIC18F26K20T-I/ML033  
PIC18F26K20T-I/ML034  
PIC18F26K20T-I/ML035  
PIC18F26K20T-I/ML040  
PIC18F26K20T-I/ML043  
PIC18F26K20T-I/ML045  
PIC18F26K20T-I/ML046  
PIC18F26K20T-I/ML047  
PIC18F26K20T-I/ML048  
PIC18F26K20T-I/ML049  
PIC18F26K20T-I/ML050  
PIC18F26K20T-I/ML051  
PIC18F26K20T-I/ML052  
PIC18F26K20T-I/ML053  
PIC18F26K20T-I/ML054  
PIC18F26K20T-I/ML055  
PIC18F26K20T-I/ML056  
PIC18F26K20T-I/ML057  
PIC18F26K20T-I/ML  
PIC18F26K20T-I/MLV03  
PIC18F26K20T-I/MLVAO  
PIC18F26K20T-I/SS  
PIC18F26K20T-I/SSLPR  
PIC18F26K20T-I/SSVAO  
PIC18F26K20T-I/SO  
PIC18F26K20T-E/MLV02  
PIC18F45K20-E/P  
PIC18F45K20-E/PT  
PIC18F45K20-I/P  
PIC18F45K20-I/MV  
PIC18F45K20-I/ML  
PIC18F45K20-I/MLC01  
PIC18F45K20-I/MLC05  
PIC18F45K20-I/PT  
PIC18F45K20-I/PTC07  
PIC18F45K20-I/PTVAO  
PIC18F45K20T-I/MV  
PIC18F45K20T-I/ML  
PIC18F45K20T-I/MLC01  
PIC18F45K20T-I/MLC05  
PIC18F45K20T-I/MLV01  
PIC18F45K20T-I/PT  
PIC18F45K20T-I/PTC07

PIC18F45K20T-I/PTVAO  
PIC18F45K22-E/P  
PIC18F45K22-E/MV  
PIC18F45K22-E/ML  
PIC18F45K22-E/PT  
PIC18F45K22-E/PTVAO  
PIC18F45K22-I/P  
PIC18F45K22-I/MV  
PIC18F45K22-I/ML  
PIC18F45K22-I/PT  
PIC18F45K22-I/PTVAO  
PIC18F45K22T-I/MV  
PIC18F45K22T-I/ML  
PIC18F45K22T-I/PT  
PIC18F45K22T-E/PTVAO  
PIC18LF45K22-E/P  
PIC18LF45K22-E/MV  
PIC18LF45K22-E/PT  
PIC18LF45K22-E/PTVAO  
PIC18LF45K22-I/P  
PIC18LF45K22-I/MV  
PIC18LF45K22-I/ML  
PIC18LF45K22-I/PT  
PIC18LF45K22T-I/MV  
PIC18LF45K22T-I/ML  
PIC18LF45K22T-I/PT  
PIC18LF45K22T-E/PTVAO  
PIC18F26K80-E/MM  
PIC18F26K80-E/MMVAO  
PIC18F26K80-E/SP  
PIC18F26K80-E/SS  
PIC18F26K80-E/SSV06  
PIC18F26K80-E/SSVAO  
PIC18F26K80-E/SO  
PIC18F45K80-E/P  
PIC18F46K80-E/P  
PIC18F45K80-E/ML  
PIC18F46K80-E/ML  
PIC18F45K80-E/PT  
PIC18F46K80-E/PT  
PIC18F45K80-E/PTVAO  
PIC18F46K80-E/PTVAO  
PIC18F26K80-I/MM  
PIC18F26K80-I/SP  
PIC18F26K80-I/SPREL  
PIC18F26K80-I/SS  
PIC18F26K80-I/SSV15  
PIC18F26K80-I/SSV22  
PIC18F26K80-I/SSVAO

PIC18F26K80-I/SO  
PIC18F45K80-I/P  
PIC18F46K80-I/P  
PIC18F45K80-I/ML  
PIC18F46K80-I/ML  
PIC18F45K80-I/PT021  
PIC18F45K80-I/PT  
PIC18F46K80-I/PT  
PIC18F45K80-I/PTVAO  
PIC18F46K80-I/PTVAO  
PIC18F26K80T-H/MMVAO  
PIC18F26K80T-H/SSV11  
PIC18F26K80T-H/SSV24  
PIC18F26K80T-H/SSVAO  
PIC18F45K80T-H/PTVAO  
PIC18F26K80-H/MM  
PIC18F26K80-H/MMVAO  
PIC18F26K80-H/SS  
PIC18F26K80-H/SSV11  
PIC18F45K80-H/ML  
PIC18F46K80-H/ML  
PIC18F45K80-H/PT  
PIC18F46K80-H/PT  
PIC18F45K80-H/PTVAO  
PIC18F26K80T-I/MM  
PIC18F26K80T-I/MMVAO  
PIC18F26K80T-I/SS  
PIC18F26K80T-I/SSV07  
PIC18F26K80T-I/SSVAO  
PIC18F26K80T-I/SO  
PIC18F45K80T-I/ML  
PIC18F46K80T-I/ML  
PIC18F45K80T-I/PT021  
PIC18F46K80T-I/PT026  
PIC18F46K80T-I/PT028  
PIC18F46K80T-I/PT029  
PIC18F46K80T-I/PT035  
PIC18F45K80T-I/PT  
PIC18F46K80T-I/PT  
PIC18F46K80T-I/PTV10  
PIC18F46K80T-I/PTV11  
PIC18F45K80T-I/PTV12  
PIC18F45K80T-I/PTVAO  
PIC18F46K80T-I/PTVAO  
PIC18F26K80T-E/MM  
PIC18F26K80T-E/MMV01  
PIC18F26K80T-E/MMV05  
PIC18F26K80T-E/MMV09  
PIC18F26K80T-E/MMV23

PIC18F26K80T-E/MMV26  
PIC18F26K80T-E/MMVAO  
PIC18F26K80T-E/SS  
PIC18F26K80T-E/SSV06  
PIC18F26K80T-E/SSV14  
PIC18F26K80T-E/SSVAO  
PIC18F26K80T-E/SO  
PIC18F45K80T-E/ML  
PIC18F46K80T-E/ML  
PIC18F45K80T-E/PT  
PIC18F46K80T-E/PT  
PIC18F45K80T-E/PTVAO  
PIC18F46K80T-E/PTVAO  
PIC18LF26K80-I/MM  
PIC18LF26K80-I/MMC01  
PIC18LF26K80-I/SP  
PIC18LF26K80-I/SS  
PIC18LF26K80-I/SO  
PIC18LF45K80-I/P  
PIC18LF46K80-I/P  
PIC18LF45K80-I/ML  
PIC18LF46K80-I/ML  
PIC18LF45K80-I/PT  
PIC18LF46K80-I/PT  
PIC18LF26K80T-I/MMC01  
PIC18LF45K80T-I/ML  
PIC18LF45K80T-I/PT  
PIC18LF46K80T-I/PT  
PIC18F46K22-E/P  
PIC18F46K22-E/MV  
PIC18F46K22-E/ML  
PIC18F46K22-E/PT  
PIC18F46K22-E/PTVAO  
PIC18F46K22-I/P  
PIC18F46K22-I/MV  
PIC18F46K22-I/ML  
PIC18F46K22-I/PT  
PIC18F46K22T-I/MV  
PIC18F46K22T-I/ML  
PIC18F46K22T-I/PT020  
PIC18F46K22T-I/PT022  
PIC18F46K22T-I/PT  
PIC18F46K22T-E/MV028  
PIC18F46K22T-E/MV029  
PIC18F46K22T-E/MV030  
PIC18F46K22T-E/MV032  
PIC18F46K22T-E/MV  
PIC18F46K22T-E/ML  
PIC18F46K22T-E/PT

PIC18F46K22T-E/PTV01  
PIC18F46K22T-E/PTVAO  
PIC18LF46K22-E/P  
PIC18LF46K22-E/MV  
PIC18LF46K22-E/ML  
PIC18LF46K22-E/PT  
PIC18LF46K22-I/P  
PIC18LF46K22-I/MV  
PIC18LF46K22-I/ML  
PIC18LF46K22-I/PT  
PIC18LF46K22-I/PTVAO  
PIC18LF46K22T-I/MV022  
PIC18LF46K22T-I/MV  
PIC18LF46K22T-I/MVV01  
PIC18LF46K22T-I/ML  
PIC18LF46K22T-I/MLV02  
PIC18LF46K22T-I/MLVAO  
PIC18LF46K22T-I/PT024  
PIC18LF46K22T-I/PT  
PIC18LF46K22T-I/PTC01  
PIC18LF46K22T-I/PTVAO  
PIC18LF46K22T-E/PT  
PIC18LF46K22T-E/PTVAO  
PIC18F26K22-E/SP  
PIC18F26K22-E/ML  
PIC18F26K22-E/SS  
PIC18F26K22-E/SSV02  
PIC18F26K22-E/SSVAO  
PIC18F26K22-E/SO  
PIC18F26K22-I/SP  
PIC18F26K22-I/ML  
PIC18F26K22-I/MLC03  
PIC18F26K22-I/SS025  
PIC18F26K22-I/SS  
PIC18F26K22-I/SSC04  
PIC18F26K22-I/SSVAO  
PIC18F26K22-I/SO029  
PIC18F26K22-I/SO  
PIC18F26K22-I/SOC02  
PIC18F26K22T-I/ML026  
PIC18F26K22T-I/ML027  
PIC18F26K22T-I/ML030  
PIC18F26K22T-I/ML032  
PIC18F26K22T-I/ML  
PIC18F26K22T-I/MLC03  
PIC18F26K22T-I/SS025  
PIC18F26K22T-I/SS  
PIC18F26K22T-I/SSC04  
PIC18F26K22T-I/SSVAO



PIC18F26K22T-I/SO022  
PIC18F26K22T-I/SO029  
PIC18F26K22T-I/SO  
PIC18F26K22T-I/SOC02  
PIC18F26K22T-E/ML  
PIC18F26K22T-E/MLV01  
PIC18F26K22T-E/MLVAO  
PIC18F26K22T-E/SS  
PIC18F26K22T-E/SSVAO  
PIC18LF26K22-E/SP  
PIC18LF26K22-E/ML  
PIC18LF26K22-E/SS  
PIC18LF26K22-I/SP  
PIC18LF26K22-I/ML  
PIC18LF26K22-I/MLC03  
PIC18LF26K22-I/MLC04  
PIC18LF26K22-I/SS  
PIC18LF26K22-I/SSC03  
PIC18LF26K22-I/SSVAO  
PIC18LF26K22-I/SO  
PIC18LF26K22-I/SOC01  
PIC18LF26K22T-I/ML  
PIC18LF26K22T-I/MLC03  
PIC18LF26K22T-I/MLC04  
PIC18LF26K22T-I/SS021  
PIC18LF26K22T-I/SS022  
PIC18LF26K22T-I/SS  
PIC18LF26K22T-I/SSC03  
PIC18LF26K22T-I/SSVAO  
PIC18LF26K22T-I/SO  
PIC18LF26K22T-I/SOC01  
PIC18LF26K22T-E/ML  
PIC18LF26K22T-E/MLV01  
PIC18LF26K22T-E/MLVAO  
PIC18F45K50-E/P  
PIC18F45K50-E/MV  
PIC18F45K50-E/PT  
PIC18F45K50-I/P  
PIC18F45K50-I/MV  
PIC18F45K50-I/PT  
PIC18F45K50T-I/MV  
PIC18F45K50T-I/PT  
PIC18LF45K50-E/P  
PIC18LF45K50-E/MV  
PIC18LF45K50-I/P  
PIC18LF45K50-I/MV  
PIC18LF45K50-I/PT  
PIC18LF45K50T-I/MV  
PIC18LF45K50T-I/PT

PIC18F26K40-E/SP  
PIC18LF26K40-E/SP  
PIC18F26K40-E/ML  
PIC18LF26K40-E/ML  
PIC18F26K40-E/MLVAO  
PIC18F26K40-E/SS  
PIC18LF26K40-E/SS  
PIC18F26K40-E/SSVAO  
PIC18LF26K40-E/SSVAO  
PIC18F26K40-E/SO  
PIC18LF26K40-E/SO  
PIC18F26K40-E/MV  
PIC18LF26K40-E/MV  
PIC18F45K40-E/P  
PIC18F46K40-E/P  
PIC18LF45K40-E/P  
PIC18LF46K40-E/P  
PIC18F45K40-E/MV  
PIC18F46K40-E/MV  
PIC18LF45K40-E/MV  
PIC18LF46K40-E/MV  
PIC18LF46K40-E/MVVAO  
PIC18F45K40-E/ML  
PIC18F46K40-E/ML  
PIC18LF45K40-E/ML  
PIC18LF46K40-E/ML  
PIC18F45K40-E/PT  
PIC18F46K40-E/PT  
PIC18LF45K40-E/PT  
PIC18LF46K40-E/PT  
PIC18F46K40-E/PTVAO  
PIC18F26K40-I/SP  
PIC18LF26K40-I/SP  
PIC18F26K40-I/ML  
PIC18LF26K40-I/ML  
PIC18F26K40-I/SSC03  
PIC18F26K40-I/SS  
PIC18LF26K40-I/SS  
PIC18F26K40-I/SSV01  
PIC18F26K40-I/SO  
PIC18LF26K40-I/SO  
PIC18F26K40-I/MV  
PIC18LF26K40-I/MV  
PIC18F26K40-I/MVVAO  
PIC18F45K40-I/P  
PIC18F46K40-I/P  
PIC18LF45K40-I/P  
PIC18LF46K40-I/P  
PIC18LF46K40-I/MVC02

PIC18F45K40-I/MV  
PIC18F46K40-I/MV  
PIC18LF45K40-I/MV  
PIC18LF46K40-I/MV  
PIC18F45K40-I/ML  
PIC18F46K40-I/ML  
PIC18LF45K40-I/ML  
PIC18LF46K40-I/ML  
PIC18F45K40-I/PT  
PIC18F46K40-I/PT  
PIC18LF45K40-I/PT  
PIC18LF46K40-I/PT  
PIC18F45K40-I/PTV02  
PIC18F46K40-I/PTV03  
PIC18F26K40T-I/ML020  
PIC18F26K40T-I/ML  
PIC18LF26K40T-I/ML  
PIC18F26K40T-I/SSC03  
PIC18F26K40T-I/SS  
PIC18LF26K40T-I/SS  
PIC18F26K40T-I/SSV01  
PIC18F26K40T-I/SO  
PIC18LF26K40T-I/SO  
PIC18F26K40T-I/MV  
PIC18LF26K40T-I/MV  
PIC18F26K40T-I/MVVAO  
PIC18LF46K40T-I/MVC02  
PIC18F45K40T-I/MV  
PIC18F46K40T-I/MV  
PIC18LF45K40T-I/MV  
PIC18LF46K40T-I/MV  
PIC18F45K40T-I/ML  
PIC18F46K40T-I/ML  
PIC18LF45K40T-I/ML  
PIC18LF46K40T-I/ML  
PIC18F45K40T-I/PT  
PIC18F46K40T-I/PT  
PIC18LF45K40T-I/PT  
PIC18LF46K40T-I/PT  
PIC18F26K40T-E/ML  
PIC18F26K40T-E/MLVAO  
PIC18F26K40T-E/SS  
PIC18LF26K40T-E/SSV04  
PIC18F26K40T-E/SSVAO  
PIC18LF26K40T-E/SSVAO  
PIC18F26K40T-E/MV  
PIC18F45K40T-E/MV  
PIC18LF46K40T-E/MV  
PIC18F45K40T-E/MVVAO

PIC18F46K40T-E/MVVAO  
PIC18F46K40T-E/MLC04  
PIC18F46K40T-E/ML  
PIC18F46K40T-E/PT  
PIC18LF46K40T-E/PT  
PIC18F46K40T-E/PTVAO  
PIC18F26K83-E/5NVAO  
PIC18F26K83-E/SP  
PIC18LF26K83-E/SP  
PIC18F26K83-E/ML  
PIC18LF26K83-E/ML  
PIC18F26K83-E/MLVAO  
PIC18F26K83-E/MX  
PIC18LF26K83-E/MX  
PIC18F26K83-E/SS  
PIC18LF26K83-E/SS  
PIC18F26K83-E/SSVAO  
PIC18F26K83-E/SO  
PIC18LF26K83-E/SO  
PIC18F26K83-I/SP  
PIC18LF26K83-I/SP  
PIC18F26K83-I/ML  
PIC18LF26K83-I/ML  
PIC18F26K83-I/MX  
PIC18LF26K83-I/MX  
PIC18F26K83-I/SS  
PIC18LF26K83-I/SS  
PIC18F26K83-I/SSVAO  
PIC18F26K83-I/SO  
PIC18LF26K83-I/SO  
PIC18F26K83T-I/ML  
PIC18LF26K83T-I/ML  
PIC18F26K83T-I/MX  
PIC18LF26K83T-I/MX  
PIC18F26K83T-I/SS020  
PIC18F26K83T-I/SS  
PIC18LF26K83T-I/SS  
PIC18F26K83T-I/SSVAO  
PIC18F26K83T-I/SO  
PIC18LF26K83T-I/SO  
PIC18F26K83T-E/5NVAO  
PIC18F26K42-E/SP  
PIC18LF26K42-E/SP  
PIC18F26K42-E/ML510  
PIC18F26K42-E/ML511  
PIC18F26K42-E/ML  
PIC18LF26K42-E/ML  
PIC18F26K42-E/MLVAO  
PIC18F26K42-E/MX

PIC18LF26K42-E/MX  
PIC18F26K42-E/SS  
PIC18LF26K42-E/SS  
PIC18F26K42-E/SSVAO  
PIC18F26K42-E/SO  
PIC18LF26K42-E/SO  
PIC18LF55K42-E/MV  
PIC18F55K42-E/MV  
PIC18LF56K42-E/MV  
PIC18F56K42-E/MV  
PIC18LF45K42-E/P  
PIC18F45K42-E/P  
PIC18LF46K42-E/P  
PIC18F46K42-E/P  
PIC18LF45K42-E/MV  
PIC18F45K42-E/MV  
PIC18LF46K42-E/MV  
PIC18F46K42-E/MV  
PIC18F46K42-E/MVVAO  
PIC18LF45K42-E/ML  
PIC18F45K42-E/ML  
PIC18LF46K42-E/ML  
PIC18F46K42-E/ML  
PIC18LF45K42-E/PT  
PIC18F45K42-E/PT  
PIC18LF46K42-E/PT  
PIC18F46K42-E/PT  
PIC18LF55K42-E/PT  
PIC18F55K42-E/PT  
PIC18LF56K42-E/PT  
PIC18F56K42-E/PT  
PIC18F26K42-I/SP  
PIC18LF26K42-I/SP  
PIC18F26K42-I/ML  
PIC18LF26K42-I/ML  
PIC18F26K42-I/MX  
PIC18LF26K42-I/MX  
PIC18F26K42-I/SS  
PIC18LF26K42-I/SS  
PIC18F26K42-I/SO  
PIC18LF26K42-I/SO  
PIC18LF55K42-I/MV  
PIC18F55K42-I/MV  
PIC18LF56K42-I/MV  
PIC18F56K42-I/MV  
PIC18LF45K42-I/P  
PIC18F45K42-I/P  
PIC18LF46K42-I/P  
PIC18F46K42-I/P

PIC18LF45K42-I/MV  
PIC18F45K42-I/MV  
PIC18LF46K42-I/MV  
PIC18F46K42-I/MV  
PIC18LF45K42-I/ML  
PIC18F45K42-I/ML  
PIC18LF46K42-I/ML  
PIC18F46K42-I/ML  
PIC18LF45K42-I/PT  
PIC18F45K42-I/PT  
PIC18LF46K42-I/PT  
PIC18F46K42-I/PT  
PIC18LF55K42-I/PT  
PIC18F55K42-I/PT  
PIC18LF55K42-I/PTC01  
PIC18LF56K42-I/PTC02  
PIC18LF56K42-I/PT  
PIC18F56K42-I/PT  
PIC18F26K42T-I/ML  
PIC18LF26K42T-I/ML  
PIC18F26K42T-I/MX  
PIC18LF26K42T-I/MX  
PIC18F26K42T-I/SS  
PIC18LF26K42T-I/SS  
PIC18F26K42T-I/SO  
PIC18LF26K42T-I/SO  
PIC18LF55K42T-I/MV  
PIC18F55K42T-I/MV  
PIC18LF56K42T-I/MV  
PIC18F56K42T-I/MV  
PIC18LF45K42T-I/MV  
PIC18F45K42T-I/MV  
PIC18LF46K42T-I/MV  
PIC18F46K42T-I/MV  
PIC18F45K42T-I/MVVAO  
PIC18LF45K42T-I/ML  
PIC18F45K42T-I/ML  
PIC18LF46K42T-I/ML  
PIC18F46K42T-I/ML  
PIC18LF45K42T-I/PT  
PIC18F45K42T-I/PT  
PIC18LF46K42T-I/PT  
PIC18F46K42T-I/PT  
PIC18LF55K42T-I/PT  
PIC18F55K42T-I/PT  
PIC18LF55K42T-I/PTC01  
PIC18LF56K42T-I/PTC02  
PIC18LF56K42T-I/PT  
PIC18F56K42T-I/PT

PIC18F26K42T-E/ML511  
PIC18F26K42T-E/MLVAO  
PIC18F55K42T-E/MV  
PIC18F56K42T-E/MV  
PIC18F45K42T-E/MVV02  
PIC18LF26J50-I/SP  
PIC18F26J50-I/SP  
PIC18LF26J50-I/ML  
PIC18F26J50-I/ML  
PIC18LF26J50-I/SS  
PIC18F26J50-I/SS  
PIC18F26J50-I/SO  
PIC18LF46J50-I/ML  
PIC18F46J50-I/ML  
PIC18F45J50-I/ML  
PIC18LF46J50-I/PT  
PIC18F46J50-I/PT  
PIC18LF45J50-I/PT  
PIC18F45J50-I/PT  
PIC18F46J50-I/PTREL  
PIC18F26J50T-I/ML  
PIC18F26J50T-I/SS033  
PIC18F26J50T-I/SS034  
PIC18F26J50T-I/SS  
PIC18F26J50T-I/SO  
PIC18F46J50T-I/ML  
PIC18F46J50T-I/PT031  
PIC18F46J50T-I/PT032  
PIC18F46J50T-I/PT  
PIC18F45J50T-I/PT  
PIC18LF26J11-I/SP  
PIC18F26J11-I/SP  
PIC18LF26J11-I/ML  
PIC18F26J11-I/ML  
PIC18LF26J11-I/SS  
PIC18F26J11-I/SS  
PIC18LF26J11-I/SO  
PIC18F26J11-I/SO  
PIC18LF46J11-I/ML  
PIC18F46J11-I/ML  
PIC18F45J11-I/ML  
PIC18LF46J11-I/PT  
PIC18F46J11-I/PT  
PIC18F45J11-I/PT  
PIC18F26J11T-I/ML  
PIC18F26J11T-I/SS  
PIC18LF46J11T-I/ML  
PIC18F46J11T-I/ML  
PIC18F46J11T-I/PT

PIC18F45J11T-I/PT  
PIC18LF26J53-I/SP  
PIC18F26J53-I/SP  
PIC18LF26J53-I/ML  
PIC18F26J53-I/ML  
PIC18LF26J53-I/SS  
PIC18F26J53-I/SS  
PIC18LF26J53-I/SO  
PIC18F26J53-I/SO  
PIC18LF46J53-I/ML  
PIC18F46J53-I/ML  
PIC18LF46J53-I/PT  
PIC18F46J53-I/PT  
PIC18F46J53T-I/PT  
PIC18LF26J13-I/SP  
PIC18F26J13-I/SP  
PIC18LF26J13-I/ML  
PIC18F26J13-I/ML  
PIC18LF26J13-I/SS  
PIC18F26J13-I/SS  
PIC18LF26J13-I/SO  
PIC18F26J13-I/SO  
PIC18LF46J13-I/ML  
PIC18F46J13-I/ML  
PIC18LF46J13-I/PT  
PIC18F46J13-I/PT  
PIC18LF45J10-I/P  
PIC18F45J10-I/P  
PIC18F45J10-I/PREL  
PIC18LF45J10-I/ML  
PIC18F45J10-I/ML  
PIC18F45J10-I/PT  
PIC18F45J10T-I/ML  
PIC18F45J10T-I/PT  
PIC18LF4553-I/PT  
PIC18F4553-I/PT  
PIC18F4550T-I/MLVAO  
PIC18F4550T-I/PT028  
PIC18LF4550T-I/PT  
PIC18F4550T-I/PT  
PIC18LF4550T-I/ML  
PIC18F4550T-I/ML  
PIC18F4520-I/PTC05  
PIC18F4680T-I/PT041  
PIC18F4680T-I/PT042  
PIC18F4680T-I/PT043  
PIC18F4680T-I/PT044  
PIC18F46K40-I/PTVAO



## PIC18(L)F26/45/46/55/56K42 Family Silicon Errata and Data Sheet Clarification

The PIC18(L)F26/45/46/55/56K42 family devices that you have received conform functionally to the current Device Data Sheet (DS40001919F), except for the anomalies described in this document.

The silicon issues discussed in the following pages are for silicon revisions with the Device and Revision IDs listed in [Table 1](#). The silicon issues are summarized in [Table 2](#).


The errata described in this document will be addressed in future revisions of the PIC18(L)F26/45/46/55/56K42 silicon.

**Note:** This document summarizes all silicon errata issues from all revisions of silicon, previous as well as current. Only the issues indicated in the last column of [Table 2](#) apply to the current silicon revision (**A3**).

Data Sheet clarifications and corrections start on [page 11](#), following the discussion of silicon issues.

The silicon revision level can be identified using the current version of MPLAB® IDE and Microchip's programmers, debuggers, and emulation tools, which are available at the Microchip corporate website ([www.microchip.com](http://www.microchip.com)).

For example, to identify the silicon revision level using MPLAB IDE in conjunction with a hardware debugger:

1. Using the appropriate interface, connect the device to the hardware debugger.
2. Open an MPLAB IDE project.
3. Configure the MPLAB IDE project for the appropriate device and hardware debugger.
4. For MPLAB X IDE, select *Window > Dashboard* and click the **Refresh Debug Tool Status** icon (  ).
5. Depending on the development tool used, the part number *and* Device Revision ID value appear in the **Output** window.

**Note:** If you are unable to extract the silicon revision level, please contact your local Microchip sales office for assistance.

The DEVID/REVID values for the various PIC18(L)F26/45/46/55/56K42 silicon revisions are shown in [Table 1](#).

**TABLE 1: SILICON DEVREV VALUES**

Part Number	Device ID<13:0> <sup>(1), (2)</sup>	Revision ID for Silicon Revision		
		A1	A2	A3
PIC18F26K42	6C60h	A001	A002	A003
PIC18F45K42	6C20h	A001	A002	A003
PIC18F46K42	6C00h	A001	A002	A003
PIC18F55K42	6BC0h	A001	A002	A003
PIC18F56K42	6BA0h	A001	A002	A003
PIC18LF26K42	6DA0h	A001	A002	A003
PIC18LF45K42	6D60h	A001	A002	A003
PIC18LF46K42	6D40h	A001	A002	A003
PIC18LF55K42	6D00h	A001	A002	A003
PIC18LF56K42	6CE0h	A001	A002	A003

**Note 1:** The Revision ID is located in addresses 3FFFFCh-3FFFFDh and Device ID is located in addresses 3FFFFEh-3FFFFFh.

**2:** Refer to the “PIC18(L)F26/45/46/55/56K42 Memory Programming Specification” (DS40001886) for detailed information on Device and Revision IDs for your specific device.

**TABLE 2: SILICON ISSUE SUMMARY**

Module	Feature	Item No.	Issue Summary	Affected Revisions <sup>(1)</sup>		
				A1	A2	A3
Electrical Specifications	SMBus 2.0	1.1	SMBus 2.0 logic levels.	X		
	SMBus 3.0	1.2	SMBus 3.0 logic levels.	X	X	X
	Min VDD specification for LF devices	1.3	NVM access on LF devices may not work properly at specified voltage levels and temperatures.	X	X	X
	Fixed Voltage Reference (FVR) accuracy	1.4	FVR output tolerance may be higher than specified at temperatures below -20°C.	X	X	X
Signal Measurement Timer (SMT)	MFINTOSC clock sources into SMT	2.1	MFINTOSC clock sources into the SMT are not functional.	X	X	X
Direct Memory Access (DMA)	DMA reads from data EEPROM	3.1	DMA reads from data EEPROM does not operate.	X		
	DMA in Doze mode	3.2	DMA transfers may not work when CPU is in Doze mode.	X	X	
Universal Asynchronous Receiver Transmitter (UART)	BRGS Select	4.1	BRGS Select feature not functional in DALI mode.		X	X
	Stop bit interrupt flag	4.2	Stop bit interrupt flag functionality not available.	X		
	Auto-baud	4.3	The first character after auto-baud may be corrupted.	X	X	X
I2C	I <sup>2</sup> C receive buffer	5.1	Received data is transferred into the I2CxRXB buffer on an incorrect clock edge.	X	X	X
	I <sup>2</sup> C Start/Stop Flags	5.2	I <sup>2</sup> C Start and/or Stop flags may be set when I <sup>2</sup> C is enabled.	X	X	X
Nonvolatile Memory (NVM) Control	WRERR bit functionality	6.1	The WRERR bit cannot be cleared in hardware after being set once.	X	X	
Windowed Watchdog Timer (WWDT)	WWDT operation in Doze mode	7.1	Window violation occurs when WWDT operated in Doze mode.	X	X	
Power-Saving Operation Modes	Low-Power Sleep mode	8.1	Low-power Sleep mode does not operate at 3.1V < VDD < 3.3V.	X	X	
Analog-to-Digital Converter with Computation (ADC2)	ADC conversion	9.1	The 12-bit ADC shorts briefly at the beginning of the ADC conversion stage.	X		
	Burst Average mode Double Sampling	9.2	The ADC <sup>2</sup> does not trigger the second conversion when operated in non-continuous double-sampling Burst Average mode.	X	X	
	ADC conversion in FOSC mode	9.3	ADC does not complete conversion successfully in FOSC mode.	X		
	Double Sample Conversions	9.4	An unexpected acquisition time is added between the first and second conversions.	X	X	X
Instruction Set	MOVFF/MOVSF instruction	10.1	MOVFF/MOVSF may corrupt destination.	X	X	X
Program Flash Memory	Endurance of PFM cell for LF devices	11.1	Endurance of the PFM cell is lower than specified.	X	X	X
In-Circuit Debugging (ICD)	Software breakpoints	12.1	Software breakpoints are not available.	X	X	X

**TABLE 2: SILICON ISSUE SUMMARY**

Module	Feature	Item No.	Issue Summary	Affected Revisions <sup>(1)</sup>		
				A1	A2	A3
Central Processing Unit (CPU)	FSR Shadow Registers	13.1	FSR Shadow Registers are not writable.	X	X	X

**Note 1:** Only those issues indicated in the last column apply to the current silicon revision.

## Silicon Errata Issues

**Note:** This document summarizes all silicon errata issues from all revisions of silicon, previous as well as current. Only the issues indicated by the shaded column in the following tables apply to the current silicon revision (**A3**).

### 1. Module: Electrical Specifications

#### 1.1 SMBus 2.0

The SMBus 2.0 V<sub>IL</sub> specification (Parameter D304) at 125°C is 0.7V.

#### Work around

None.

#### Affected Silicon Revisions

A1	A2	A3					
X							

#### 1.2 SMBus 3.0

The SMBus 3.0 V<sub>IL</sub> specification (Parameter D305) is temperature and V<sub>DD</sub> dependent. Refer to the table below.

Temperature	V <sub>DD</sub>	D305 SMBus 3.0 V <sub>IL</sub> Specification
-40°C	1.8V	0.6V
-40°C	5.5V	0.8V
25°C	1.8V	0.6V
25°C	5.5V	0.8V
85°C	1.8V	0.6V
85°C	5.5V	0.7V
125°C	1.8V	0.5V
125°C	5.5V	0.7V

#### Work around

None.

#### Affected Silicon Revisions

A1	A2	A3					
X	X	X					

## 1.3 Min VDD Specification for LF Devices for A3 Rev

VDDMIN for LF devices has changed for temperatures below +25°C as shown below in **bold**.

PIC18LF26/45/46/55/56K42			Standard Operating Conditions (unless otherwise stated)				
PIC18F26/45/46/55/56K42							
Param. No.	Sym.	Characteristic	Min.	Typ.†	Max.	Units	Conditions
<b>Supply Voltage</b>							
D002	VDD		<b>2.0</b>	—	3.6	V	Fosc ≤ 16 MHz ( <b>-40°C to &lt;+25°C</b> )
			<b>1.8</b>	—	3.6	V	Fosc ≤ 16 MHz ( <b>≥+25°C to +125°C</b> )
			2.5	—	3.6	V	Fosc > 16 MHz and Fosc ≤ 32 MHz
			2.7	—	3.6	V	Fosc > 32 MHz
D002	VDD		2.3	—	5.5	V	Fosc ≤ 16 MHz
			2.5	—	5.5	V	Fosc > 16 MHz and Fosc ≤ 32 MHz
			2.7	—	5.5	V	Fosc > 32 MHz

### Work around

None.

### Affected Silicon Revisions

A1	A2	A3					
X	X	X					

## 1.4 Fixed Voltage Reference (FVR) Accuracy

At temperatures below -20°C, the output voltage for the FVR may be greater than the levels specified in the data sheet. This will apply to all three gain amplifier settings (1X, 2X, 4X). The affected parameter numbers found in the data sheet are: FVR01 (1X gain setting), FVR02 (2X gain setting), and FVR03 (4X gain setting).

### Work around

At temperatures above -20°C, the stated tolerances in the data sheet remain in effect. Operate the FVR only at temperatures above -20°C.

### Affected Silicon Revisions

A1	A2	A3					
X	X	X					

## 2. Module: Signal Measurement Timer (SMT)

### 2.1 MFINTOSC Clock Sources into SMT

The Signal Measurement Timer does not operate when the MFINTOSC is selected as the clock source (i.e. CSEL = 0b100 and 0b101).

#### Work around

The MFINTOSC does not start up automatically. User software needs to manually enable the MFINTOSC by setting the MFOEN bit in the OSCEN register. The MFINTOSC will remain enabled as long as MFOEN bit is set.

#### Affected Silicon Revisions

A1	A2	A3					
X	X	X					

## 3. Module: Direct Memory Access (DMA)

### 3.1 DMA Reads from Data EEPROM

The DMA modules do not operate when configured to access the Data EEPROM (i.e., SMR<1:0> = 1x). The destination gets written to 0x00.

#### Work around

None. NVMCON reads work as described.

#### Affected Silicon Revisions

A1	A2	A3					
X							

### 3.2 DMA in Doze Mode

When the CPU is operated in Doze mode, DMA transfers may not work as expected.

#### Work around

None.

#### Affected Silicon Revisions

A1	A2	A3					
X	X						

## 4. Module: Universal Asynchronous Receiver Transmitter (UART)

### 4.1 Baud Rate Generator Speed Select

The Baud Rate Generator Speed Select feature (the BRGS bit in the UxCON0 register) in DALI mode is not functional. The Baud Rate Generator always operates at normal speed with 16 baud clocks per bit in DALI mode.

#### Work around

When using UART in DALI mode, operate the Baud Rate Generator in normal speed (BRGS = 0) only and use the following formula to calculate the UxBRGH:L register value:

$$U_xBRGH:L = \frac{F_{OSC}}{16 \times \text{Desired Baud Rate}} - 1$$

Example: To obtain the desired baud rate of 1200 at Fosc = 64 MHz,

$$U_xBRGH:L = \frac{64,000,000}{16 \times 1200} - 1 = 3332$$

#### Affected Silicon Revisions

A1	A2	A3					
	X	X					

### 4.2 Stop Bit Interrupt Flag

Stop bit interrupt flag functionality is not available in the CERIF bit in revision A1.

#### Work around

Use Timer2 with HLT and connect the UART RX port to the timer Reset trigger. Set the time-out period to the desired Stop bit time (for DALI mode, this is equivalent to two Stop bits at 1200 baud = 1.66 ms). When the Stop bit is received, the timer times out notifying end of data.

#### Affected Silicon Revisions

A1	A2	A3					
X							

## 4.3 Auto-Baud

When the UART is configured as follows, then the first character received after auto-baud may be corrupted:

- The UBRG registers are cleared.
- The BRGS bit is set (Fast Baud Rate mode).
- The Stop bits are configured for two Stop bits (STP = 0b1x).

### Work around

- In asynchronous modes other than LIN: The transmitter may delay the first character by at least one character period after sending auto-baud.
- In all asynchronous modes including LIN: Clear the BRGS bit to select the normal baud rate mode.

### Affected Silicon Revisions

A1	A2	A3					
X	X	X					

## 5. Module: I<sup>2</sup>C

### 5.1 I<sup>2</sup>C Receive Buffer

When receiving data into the receive buffer I2CxRXB, the byte is transferred into the buffer on the 9th rising clock edge rather than the expected 8th falling edge. This causes both the Receive Buffer Full (RXBF) status bit and the Receive Buffer Interrupt Flag (I2CxRXIF) to also be set on the 9th rising clock edge. The Data Write Interrupt (WRIF) and Address Interrupt Flag (ADRIF) will still be set on the 8th falling clock edge. If user software is configured to interrupt (or poll) when either the WRIF bit or the ADRIF bit is set, hardware will read an empty receive buffer, set the Receive Read Error (RXRE) status flag, and a NACK will be issued.

### Work around

Do not use WRIF or ADRIF to determine when the receive buffer has received data. Instead, interrupt/poll using the I2CxRXIF interrupt bit or poll the RXBF bit. These bits are correctly set once the address/data byte has been transferred into I2CxRXB.

### Affected Silicon Revisions

A1	A2	A3					
X	X	X					

### 5.2 I<sup>2</sup>C Start and/or Stop Flags May be Set When I<sup>2</sup>C is Enabled

When I<sup>2</sup>C is enabled, erroneous Start and/or Stop conditions may be detected. This can generate erroneous I<sup>2</sup>C interrupts if enabled.

### Work around

Use the following procedure to correctly detect the Start and Stop conditions:

1. Disable Start and Stop conditions interrupt functions.
2. Enable I<sup>2</sup>C module.
3. Wait 250 ns + 6 instruction cycles (Fosc/4).
4. Clear the Start and Stop conditions interrupt flags.
5. Enable Start and Stop conditions interrupt functions if used.

```
I2CxPIEBits.SCIE = 0;
I2CxPIEBits.PCIE = 0;
I2CxCON0bits.EN = 1;
Delay();
I2CxPIRbits.SCIF = 0;
I2CxPIRbits.PCIF = 0;
I2CxPIEBits.SCIE = 1;
I2CxPIEBits.PCIE = 1;
```

### Affected Silicon Revisions

A1	A2	A3					
X	X	X					

## 6. Module: Nonvolatile Memory (NVM) Control

### 6.1 WRERR Bit Functionality

When a Reset is issued while an NVM high-voltage operation is in progress, the WRERR bit in the NVMCON1 register is set as expected. After clearing the WRERR bit, if a Reset reoccurs, the WRERR bit is set again regardless of whether an NVM operation is in progress or not. A successful write operation will clear the WRERR condition.

### Work around

None.

### Affected Silicon Revisions

A1	A2	A3					
X	X						

## 7. Module: Windowed Watchdog Timer (WWDT)

### 7.1 WWDT Operation in Doze Mode

When the CLRWDT instruction is issued in Doze mode, a window violation error occurs in WWDT even though the window is open and armed.

#### Work around

Do not operate the WWDT in Doze mode.

#### Affected Silicon Revisions

A1	A2	A3					
X	X						

## 8. Module: Power-Saving Operation Modes

### 8.1 Low-Power Sleep Mode in F Devices

The F device resets when waking up from Sleep while in Low-Power mode (VREGPM = 1 in the VREGCON register) at  $3.1V < V_{DD} < 3.3V$ .

#### Work around

- If wake-up from Sleep is needed at  $3.1V < V_{DD} < 3.3V$ , operate the F device in Normal Power mode (VREGPM = 0).
- If wake-up from Sleep is needed at  $3.1V < V_{DD} < 3.3V$ , enable the Fixed Voltage Reference (EN = 1 in the FVRCON register). This increases the current in Sleep mode by typically 7  $\mu A$ .

#### Affected Silicon Revisions

A1	A2	A3					
X	X						

## 9. Module: Analog-to-Digital Converter with Computation (ADC<sup>2</sup>)

### 9.1 ADC Conversion

At the very beginning of the ADC conversion, the input signal may briefly be pulled to ground, which in turn may take some charge out of the internal Sample-and-Hold capacitor. The problem is more pronounced on inputs with an impedance greater than 1 kOhm.

This issue will be seen when sampling the following internal channel inputs: FVR, DAC, and Temperature Indicator and when sampling external sources on an analog pin, including the CVD.

#### Work around

- When sampling the internal channel inputs, FVR, DAC, and Temperature Indicator, increase the minimum TAD time to 4  $\mu s$  to increase accuracy.
- When sampling an external source through an analog pin, keep the input impedance below 1 kOhm.
- When using the ADC in CVD mode, there is no work around.

#### Affected Silicon Revisions

A1	A2	A3					
X							



## 9.2 Burst Average Mode Double Sampling

When the ADC<sup>2</sup> is operated in Burst Average mode (MD = 0b011 in the ADCON2 register) while enabling non-continuous operation and double-sampling (CONT = 0 in the ADCON0 register and DSEN = 1 in the ADCON1 register), the value in the ADCNT register does not increment beyond 0b1 toward the value in the ADRPT register.

### Work around

When operating the ADC<sup>2</sup> in Burst Average mode with double-sampling, enable continuous operation of the module (CONT = 1 in the ADCON0 register) and set the Stop-On-Interrupt bit (SOI in the ADCON3 register). After the interrupt occurs, perform appropriate threshold calculations in the software and retrigger ADC<sup>2</sup> as necessary.

If the CPU is in Low-Power Sleep mode, alternatively the ADC<sup>2</sup> in non-continuous Burst Average mode can be operated with single ADC conversion (DSEN = 0 in the ADCON1 register) compromising noise immunity for lower power consumption by preventing the device from waking up to perform threshold calculations in the software.

### Affected Silicon Revisions

A1	A2	A3					
X	X						

## 9.3 ADC Conversion in Fosc Mode

The ADCON0.GO bit remains set and the conversion does not complete successfully when configured to operate in FOSC mode (ADCON0.CS = 0) with Fosc > 40 MHz.

### Work around

Use ADCRC as the ADC clock source (ADCON0.CS = 1).

### Affected Silicon Revisions

A1	A2	A3					
X							

## 9.4 Double Sample Conversions

When enabling a Double Sample Conversion (DSEN = 1), with no Precharge time (ADPRE = 0) and no Acquisition time (ADACQ = 0), the maximum number of cycles of acquisition time is inserted prior to the second conversion.

The first conversion will be performed as expected with no Precharge time and no Acquisition time. It is only between the first and second conversions where a maximum number of cycles of Acquisition time is performed unexpectedly.

### Work around

Method 1: Disable double conversion (DSEN = 0) and perform two single conversions back to back.

Method 2: If adding acquisition time is acceptable, then select no Precharge time, along with the desired Acquisition time.

### Affected Silicon Revisions

A1	A2	A3					
X	X	X					

## 10. Module: Instruction Set

### 10.1 MOVFF/MOVSF Instruction

When the BSR points to the last bank of the SFR region (BSR = 0x3F) and the low byte of the source or destination address of a MOVFF/MOVSF instruction equals the low byte of an indirect addressing operation register address (INDFx, POSTINCx, POSTDECx, PREINCx, PLUSWx), the operation will not be completed as expected. Either, one or more of the destination, FSR value, or location pointed to by the FSR will be corrupted, or the move will simply not occur.

#### Work around

Ensure that the BSR does not point to the last bank of the SFR region (BSR = 0x3F) when the MOVFF/MOVSF instruction is being executed.

#### Affected Silicon Revisions

A1	A2	A3						
X	X	X						

## 11. Module: Program Flash Memory

### 11.1 Endurance of PFM Cell for LF Devices

The Flash memory cell endurance specification (Parameter MEM30) for PIC18LF26/45/46/55/56K42 devices is 1K cycles.

#### Work around

None.

#### Affected Silicon Revisions

A1	A2	A3						
X	X	X						

## 12. Module: In-Circuit Debugging (ICD)

### 12.1 Software Breakpoints

When debugging code, software breakpoints will not be available.

#### Work around

None.

#### Affected Silicon Revisions

A1	A2	A3						
X	X	X						

## 13. Module: Central Processing Unit (CPU)

### 13.1 FSR Shadow Registers

Writing to the FSR Shadow Registers does not result in accurate values being stored in the registers. Consequently, reading the FSR Shadow Registers after they have been written will return inaccurate data.

#### Work around

Writes to the FSR shadow registers can be performed safely using the following steps:

1. Save regular FSR2 value into RAM
2. Write the regular FSR2 with the targeted value minus the computed offset (IR[6:0] + 1, see below)
3. Write the shadow FSRxL (data doesn't matter), this will clock the shadow FSR with the FSR computed offset value.
4. Decrement FSR2 value by 1 since FSRxH increments the address by 1 (IR[6:0])
5. Write FSRxH
6. Restore the regular FSR2 from the stored RAM value.

The FSR shadow should have the value desired and the regular FSR should have the original value.

#### Affected Silicon Revisions

A1	A2	A3						
X	X	X						

## Data Sheet Clarifications

The following typographic corrections and clarifications are to be noted for the latest version of the device data sheet (DS40001919F):

Corrections are shown in **bold**. Where possible, the original bold text formatting has been removed for clarity.

None.

## APPENDIX A: DOCUMENT REVISION HISTORY

### Rev K Document (04/2022)

Added Module 9.4 Double Sample Conversions, 13 Central Processing Unit (CPU), and 13.1 FSR Shadow Registers.

### Rev J Document (09/2021)

Added Module 5.2 I<sup>2</sup>C Start/Stop Flags.

### Rev H Document (02/2021)

Added Module 11.1 Software Breakpoints. Minor corrections.

### Rev G Document (11/2019)

Added Modules 1.4 Fixed Voltage Reference (FVR) Accuracy and 5.1 I<sup>2</sup>C Receive Buffer; Added Module 11 Program Flash Memory; Removed A2 rev in 9.3 (typo).

### Rev F Document (03/2019)

Added silicon rev. A3. Updated Module 5.1. Added sections 4.3, 8.3 and 9.1.

### Rev E Document (11/2018)

Updated Modules 3.1 and 4.1.

Data Sheet Clarifications: Deleted Module 1: Electrical Specifications.

### Rev D Document (09/2018)

Updated Table 2. Updated Item 8.1.

### Rev C Document (06/2018)

Updated Table 1 and Table 2; Added Module 4: UART; Module 3.2; Module 5: NVM Control; Module 6: WWDT; Module 7: Power-Saving Operation Modes; Added Module 8: ADC

Data Sheet Clarifications: Added Module 1: Electrical Specifications.

Other minor corrections.

### Rev B Document (10/2017)

Added Module 3: DMA to Silicon Errata Issues. Other minor corrections.

### Rev A Document (06/2017)

Initial release of this document.

---

---

**Note the following details of the code protection feature on Microchip products:**

- Microchip products meet the specifications contained in their particular Microchip Data Sheet.
- Microchip believes that its family of products is secure when used in the intended manner, within operating specifications, and under normal conditions.
- Microchip values and aggressively protects its intellectual property rights. Attempts to breach the code protection features of Microchip product is strictly prohibited and may violate the Digital Millennium Copyright Act.
- Neither Microchip nor any other semiconductor manufacturer can guarantee the security of its code. Code protection does not mean that we are guaranteeing the product is “unbreakable”. Code protection is constantly evolving. Microchip is committed to continuously improving the code protection features of our products.

---

This publication and the information herein may be used only with Microchip products, including to design, test, and integrate Microchip products with your application. Use of this information in any other manner violates these terms. Information regarding device applications is provided only for your convenience and may be superseded by updates. It is your responsibility to ensure that your application meets with your specifications. Contact your local Microchip sales office for additional support or, obtain additional support at <https://www.microchip.com/en-us/support/design-help/client-support-services>.

THIS INFORMATION IS PROVIDED BY MICROCHIP “AS IS”. MICROCHIP MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WHETHER EXPRESS OR IMPLIED, WRITTEN OR ORAL, STATUTORY OR OTHERWISE, RELATED TO THE INFORMATION INCLUDING BUT NOT LIMITED TO ANY IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE, OR WARRANTIES RELATED TO ITS CONDITION, QUALITY, OR PERFORMANCE.

IN NO EVENT WILL MICROCHIP BE LIABLE FOR ANY INDIRECT, SPECIAL, PUNITIVE, INCIDENTAL, OR CONSEQUENTIAL LOSS, DAMAGE, COST, OR EXPENSE OF ANY KIND WHATSOEVER RELATED TO THE INFORMATION OR ITS USE, HOWEVER CAUSED, EVEN IF MICROCHIP HAS BEEN ADVISED OF THE POSSIBILITY OR THE DAMAGES ARE FORESEEABLE. TO THE FULLEST EXTENT ALLOWED BY LAW, MICROCHIP’S TOTAL LIABILITY ON ALL CLAIMS IN ANY WAY RELATED TO THE INFORMATION OR ITS USE WILL NOT EXCEED THE AMOUNT OF FEES, IF ANY, THAT YOU HAVE PAID DIRECTLY TO MICROCHIP FOR THE INFORMATION.

Use of Microchip devices in life support and/or safety applications is entirely at the buyer’s risk, and the buyer agrees to defend, indemnify and hold harmless Microchip from any and all damages, claims, suits, or expenses resulting from such use. No licenses are conveyed, implicitly or otherwise, under any Microchip intellectual property rights unless otherwise stated.

For information regarding Microchip’s Quality Management Systems, please visit [www.microchip.com/quality](http://www.microchip.com/quality).

**Trademarks**

The Microchip name and logo, the Microchip logo, Adaptec, AnyRate, AVR, AVR logo, AVR Freaks, BesTime, BitCloud, CryptoMemory, CryptoRF, dsPIC, flexPWR, HELDO, IGLOO, JukeBlox, KeeLoq, Kleer, LANCheck, LinkMD, maXStylus, maXTouch, MediaLB, megaAVR, Microsemi, Microsemi logo, MOST, MOST logo, MPLAB, OptoLyzer, PIC, picoPower, PICSTART, PIC32 logo, PolarFire, Prochip Designer, QTouch, SAM-BA, SenGenuity, SpyNIC, SST, SST Logo, SuperFlash, Symmetricom, SyncServer, Tachyon, TimeSource, tinyAVR, UNI/O, Vectron, and XMEGA are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

AgileSwitch, APT, ClockWorks, The Embedded Control Solutions Company, EtherSynch, Flashtec, Hyper Speed Control, HyperLight Load, IntelliMOS, Libero, motorBench, mTouch, Powermite 3, Precision Edge, ProASIC, ProASIC Plus, ProASIC Plus logo, QuietWire, SmartFusion, SyncWorld, Temux, TimeCesium, TimeHub, TimePictra, TimeProvider, TrueTime, WinPath, and ZL are registered trademarks of Microchip Technology Incorporated in the U.S.A.

Adjacent Key Suppression, AKS, Analog-for-the-Digital Age, Any Capacitor, AnyIn, AnyOut, Augmented Switching, BlueSky, BodyCom, CodeGuard, CryptoAuthentication, CryptoAutomotive, CryptoCompanion, CryptoController, dsPICDEM, dsPICDEM.net, Dynamic Average Matching, DAM, ECAN, Espresso T1S, EtherGREEN, GridTime, IdealBridge, In-Circuit Serial Programming, ICSP, INICnet, Intelligent Paralleling, Inter-Chip Connectivity, JitterBlocker, Knob-on-Display, maxCrypto, maxView, memBrain, Mindi, MiWi, MPASM, MPF, MPLAB Certified logo, MPLIB, MPLINK, MultiTRAK, NetDetach, NVM Express, NVMe, Omniscient Code Generation, PICDEM, PICDEM.net, PICKit, PICtail, PowerSmart, PureSilicon, QMatrix, REAL ICE, Ripple Blocker, RTAX, RTG4, SAM-ICE, Serial Quad I/O, simpleMAP, SimpliPHY, SmartBuffer, SmartHLS, SMART-I.S., storClad, SQL, SuperSwitcher, SuperSwitcher II, Switchtec, SynchroPHY, Total Endurance, TSHARC, USBCheck, VariSense, VectorBlox, VeriPHY, ViewSpan, WiperLock, XpressConnect, and ZENA are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

SQTP is a service mark of Microchip Technology Incorporated in the U.S.A.

The Adaptec logo, Frequency on Demand, Silicon Storage Technology, Symmcom, and Trusted Time are registered trademarks of Microchip Technology Inc. in other countries.

GestIC is a registered trademark of Microchip Technology Germany II GmbH & Co. KG, a subsidiary of Microchip Technology Inc., in other countries.

All other trademarks mentioned herein are property of their respective companies.

© 2017-22, Microchip Technology Incorporated and its subsidiaries.

All Rights Reserved.

ISBN: 978-1-6683-0293-4



# MICROCHIP

## Worldwide Sales and Service

### AMERICAS

**Corporate Office**  
2355 West Chandler Blvd.  
Chandler, AZ 85224-6199  
Tel: 480-792-7200  
Fax: 480-792-7277  
Technical Support:  
<http://www.microchip.com/support>  
Web Address:  
[www.microchip.com](http://www.microchip.com)

#### Atlanta

Duluth, GA  
Tel: 678-957-9614  
Fax: 678-957-1455

#### Austin, TX

Tel: 512-257-3370

#### Boston

Westborough, MA  
Tel: 774-760-0087  
Fax: 774-760-0088

#### Chicago

Itasca, IL  
Tel: 630-285-0071  
Fax: 630-285-0075

#### Dallas

Addison, TX  
Tel: 972-818-7423  
Fax: 972-818-2924

#### Detroit

Novi, MI  
Tel: 248-848-4000

#### Houston, TX

Tel: 281-894-5983

#### Indianapolis

Noblesville, IN  
Tel: 317-773-8323  
Fax: 317-773-5453  
Tel: 317-536-2380

#### Los Angeles

Mission Viejo, CA  
Tel: 949-462-9523  
Fax: 949-462-9608  
Tel: 951-273-7800

#### Raleigh, NC

Tel: 919-844-7510

#### New York, NY

Tel: 631-435-6000

#### San Jose, CA

Tel: 408-735-9110  
Tel: 408-436-4270

#### Canada - Toronto

Tel: 905-695-1980  
Fax: 905-695-2078

### ASIA/PACIFIC

**Australia - Sydney**  
Tel: 61-2-9868-6733

**China - Beijing**  
Tel: 86-10-8569-7000

**China - Chengdu**  
Tel: 86-28-8665-5511

**China - Chongqing**  
Tel: 86-23-8980-9588

**China - Dongguan**  
Tel: 86-769-8702-9880

**China - Guangzhou**  
Tel: 86-20-8755-8029

**China - Hangzhou**  
Tel: 86-571-8792-8115

**China - Hong Kong SAR**  
Tel: 852-2943-5100

**China - Nanjing**  
Tel: 86-25-8473-2460

**China - Qingdao**  
Tel: 86-532-8502-7355

**China - Shanghai**  
Tel: 86-21-3326-8000

**China - Shenyang**  
Tel: 86-24-2334-2829

**China - Shenzhen**  
Tel: 86-755-8864-2200

**China - Suzhou**  
Tel: 86-186-6233-1526

**China - Wuhan**  
Tel: 86-27-5980-5300

**China - Xian**  
Tel: 86-29-8833-7252

**China - Xiamen**  
Tel: 86-592-2388138

**China - Zhuhai**  
Tel: 86-756-3210040

### ASIA/PACIFIC

**India - Bangalore**  
Tel: 91-80-3090-4444

**India - New Delhi**  
Tel: 91-11-4160-8631

**India - Pune**  
Tel: 91-20-4121-0141

**Japan - Osaka**  
Tel: 81-6-6152-7160

**Japan - Tokyo**  
Tel: 81-3-6880-3770

**Korea - Daegu**  
Tel: 82-53-744-4301

**Korea - Seoul**  
Tel: 82-2-554-7200

**Malaysia - Kuala Lumpur**  
Tel: 60-3-7651-7906

**Malaysia - Penang**  
Tel: 60-4-227-8870

**Philippines - Manila**  
Tel: 63-2-634-9065

**Singapore**  
Tel: 65-6334-8870

**Taiwan - Hsin Chu**  
Tel: 886-3-577-8366

**Taiwan - Kaohsiung**  
Tel: 886-7-213-7830

**Taiwan - Taipei**  
Tel: 886-2-2508-8600

**Thailand - Bangkok**  
Tel: 66-2-694-1351

**Vietnam - Ho Chi Minh**  
Tel: 84-28-5448-2100

### EUROPE

**Austria - Wels**  
Tel: 43-7242-2244-39  
Fax: 43-7242-2244-393

**Denmark - Copenhagen**  
Tel: 45-4485-5910  
Fax: 45-4485-2829

**Finland - Espoo**  
Tel: 358-9-4520-820

**France - Paris**  
Tel: 33-1-69-53-63-20  
Fax: 33-1-69-30-90-79

**Germany - Garching**  
Tel: 49-8931-9700

**Germany - Haan**  
Tel: 49-2129-3766400

**Germany - Heilbronn**  
Tel: 49-7131-72400

**Germany - Karlsruhe**  
Tel: 49-721-625370

**Germany - Munich**  
Tel: 49-89-627-144-0  
Fax: 49-89-627-144-44

**Germany - Rosenheim**  
Tel: 49-8031-354-560

**Israel - Ra'anana**  
Tel: 972-9-744-7705

**Italy - Milan**  
Tel: 39-0331-742611  
Fax: 39-0331-466781

**Italy - Padova**  
Tel: 39-049-7625286

**Netherlands - Drunen**  
Tel: 31-416-690399  
Fax: 31-416-690340

**Norway - Trondheim**  
Tel: 47-7288-4388

**Poland - Warsaw**  
Tel: 48-22-3325737

**Romania - Bucharest**  
Tel: 40-21-407-87-50

**Spain - Madrid**  
Tel: 34-91-708-08-90  
Fax: 34-91-708-08-91

**Sweden - Gothenberg**  
Tel: 46-31-704-60-40

**Sweden - Stockholm**  
Tel: 46-8-5090-4654

**UK - Wokingham**  
Tel: 44-118-921-5800  
Fax: 44-118-921-5820