

Product Search Data Sheet

CSTNR4M00GH5L000R0

In Production Recommended RoHS REACH

Appearance & Shape





Note: This datasheet may be out of date. Please download the latest datasheet of CSTNR4M00GH5L000R0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=CSTNR4M00GH5L000R0



MURATA's frequency adjustment and packaging technology expertise has enabled the development of the chip CERALOCK(R) with built-in load capacitors.

Features

- 1. Oscillation circuits do not require external load capacitors.
- 2. Available for a wide frequency range.
- 3. Extremely small and have a low profile.
- 4. No adjustment is necessary for oscillation circuits.
- 5. Stable supply is ensured due to not using precious

metal(Palladium).



Other Usage

Consumer/Industrial



## **Packaging Information**

| Packaging | Specifications      | Standard |
|-----------|---------------------|----------|
|           |                     | Packing  |
|           |                     | Quantity |
| R0        | 180mm Embossed Tape | 3000     |

1 of 2

## Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





CSTNR4M00GH5L000R0

Note: This datasheet may be out of date. Please download the latest datasheet of CSTNR4M00GH5L000R0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=CSTNR4M00GH5L000R0

## Specifications

| Product Type                           | Ceramic Resonator<br>(CERALOCK) |
|--|---------------------------------|
| Series                                 | CSTNR_GH5L                      |
| Frequency                              | 4.000MHz                        |
| Frequency Tolerance                    | +/-0.07% max.                   |
| Operating Temperature<br>Range         | -20°C~85°C                      |
| Frequency Shift by<br>Temperature      | +/-0.11% max.                   |
| Frequency Aging                        | +/-0.07% max.                   |
| Resonant Impedance (R1)                | 60ohm max.                      |
| Built-in Load Capacitance<br>(CL1/CL2) | 39pF                            |
| Shape                                  | SMD                             |
| Wash                                   | Not available                   |
| L x W (size)                           | 4.5x2.0mm                       |
| Mass                                   | 32.54mg                         |

2 of 2

## Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

