200 mA 36 V Input Ultra Low Supply Current VR for Automotive Applications

No. EC-332-250609

OUTLINE

The R1524x is an ultra-low supply current voltage regulator featuring 200 mA output current and 36 V input voltage. This device consists of an Output Short-circuit Protection Circuit, an Over-current Protection Circuit, and a Thermal Shutdown Circuit in addition to the basic regulator circuits. The operating temperature range is between −40°C to 125°C, and the maximum input voltage is 36 V. All these features allow this device to become an ideal power source for car accessories and ECUs.
The output voltages are internally fixed (refer to *SELECTION GUIDE*). The output voltage accuracy is ±0.6%. The packages for this device range from high-density mounting to ultra high wattage. The R1524x is offered in four packages; a 5-pin SOT-23-5, a 5-pin SOT-89-5, and a 6-pin HSOP-6J, and an 8-pin HSOP-8E package.

FEATURES

- Input Voltage Range (Maximum Rating)····· 3.5 V to 36 V (50 V)
- Operating Temperature Range ····· –40°C to 125°C
- Supply Current ····· Typ. 2.2 µA
- Standby Current····· Typ. 0.1 µA
- Dropout Voltage····· Typ. 0.6 V (I_{OUT} = 200 mA, V_{OUT} = 5.0 V)
- Output Voltage Range ····· 1.8 V / 2.5 V / 2.8 V / 3.0 V / 3.3 V / 3.4 V / 5.0 V / 5.5 V / 6.0 V / 6.4 V / 7.0 V / 7.5 V / 8.0 V / 8.5 V / 9.0 V/ 10.0 V / 10.5 V / 11.0 V / 12.0 V
  *Contact our sales representatives for other voltages.
- Output Voltage Accuracy····· ±0.6% (Ta = 25°C)
- Output Voltage Temperature-Drift Coefficient ····· Typ. ±60 ppm/°C
- Line Regulation····· Typ. 0.01%/V (V_{SET} + 1 V ≤ V_{IN} ≤ 36 V)
- Built-in Output Short-circuit Protection Circuit····· Typ. 80 mA
- Built-in Over-current Protection Circuit····· Typ. 350 mA
- Built-in Thermal Shutdown Circuit····· Thermal Shutdown Temperature: Typ. 160°C
- Ceramic capacitors are recommended to be used with this device ····· C_{OUT} = 0.1 µF or more
- Packages····· SOT-23-5, SOT-89-5, HSOP-6J, HSOP-8E

APPLICATIONS

- Power source for accessories such as car audios, car navigation systems, and ETC systems
- Power source for ECUs such as EV inverter and battery charge control unit

SELECTION GUIDE

The set output voltage, the package type, and the quality class are user-selectable.

Selection Guide


Product Name	Package	Quantity per Reel	Pb Free	Halogen Free
R1524NxxxB-TR-#E	SOT-23-5	3,000 pcs	Yes	Yes
R1524HxxxB-T1-#E	SOT-89-5	1,000 pcs	Yes	Yes
R1524SxxxB-E2-#E	HSOP-6J	1,000 pcs	Yes	Yes
R1524SxxxH-E2-#E	HSOP-8E	1,000 pcs	Yes	Yes

xxx: Specify the set output voltage (V_{SET})
1.8 V (018) / 2.5 V (025) / 2.8 V (028) / 3.0 V (030) / 3.3 V (033) / 3.4 V (034) / 5.0 V (050) / 5.5 V (055) / 6.0 V (060) / 6.4 V (064) / 7.0 V (070) / 7.5 V (075) / 8.0 V (080) / 8.5 V (085) / 9.0 V (090) / 10.0 V (100) / 10.5 V (105) / 11.0 V (110) / 12.0 V (120)
*Contact our sales representatives for other voltages.

: Quality Class


#	Operating Temperature Range	Test Temperature
A	−40°C to 125°C	25°C, High
K	−40°C to 125°C	Low, 25°C, High

BLOCK DIAGRAM




R1524x Block Diagram


PIN DESCRIPTIONS




SOT-23-5 Pin Configuration



SOT-89-5 Pin Configuration



HSOP-6J Pin Configuration



HSOP-8E Pin Configuration

SOT-23-5 Pin Descriptions

Pin No.	Symbol	Description
1	GND[2]	Ground Pin
2	GND[2]	Ground Pin
3	CE	Chip Enable Pin (Active-high)
4	V_{OUT}	Output Pin
5	V_{DD}	Input Pin

SOT-89-5 Pin Descriptions

Pin No.	Symbol	Description
1	V_{OUT}	Output Pin
2	GND[2]	Ground Pin
3	CE	Chip Enable Pin (Active-high)
4	GND[2]	Ground Pin
5	V_{DD}	Input Pin

HSOP-6J Pin Descriptions


[1] The tab on the bottom of the package enhances thermal performance and is electrically connected to GND (substrate level). It is recommended that the tab be connected to the ground plane on the board, or otherwise be left open.
[2] The GND pin must be wired together when it is mounted on board.

Pin No.	Symbol	Description
1	V_{OUT}	Output Pin
2	GND(1)	Ground Pin
3	CE	Chip Enable Pin (Active-high)
4	GND(1)	Ground Pin
5	GND(1)	Ground Pin
6	V_{DD}	Input Pin


HSOP-8E Pin Descriptions

Pin No.	Symbol	Description
1	V_{OUT}	Output Pin
2	NC	No Connection
3	NC	No Connection
4	CE	Chip Enable Pin (Active-high)
5	GND	Ground Pin
6	NC	No Connection
7	NC	No Connection
8	V_{DD}	Input Pin

PIN EQUIVALENT CIRCUIT DIAGRAMS



V_{OUT} Pin



CE Pin

(1) The GND pin must be wired together when it is mounted on board.

ABSOLUTE MAXIMUM RATINGS

Absolute Maximum Ratings

Symbol	Item		Rating	Unit
V_{IN}	Input Voltage		−0.3 to 50	V
V_{IN}	Peak Input Voltage(1)		60	V
V_{CE}	Input Voltage (CE Pin)		−0.3 to 50	V
V_{OUT}	Output Voltage		−0.3 to V_{IN} + 0.3 ≤ 50	V
I_{OUT}	Output Current		300	mA
P_D	Power Dissipation(2) (JEDEC STD.51-7 Test Land Pattern)	SOT-23-5	830	mW
		SOT-89-5	3200	
		HSOP-6J	3400	
		HSOP-8E	3600	
Tj	Junction Temperature Range		−40 to 150	°C
Tstg	Storage Temperature Range		−55 to 150	°C

ABSOLUTE MAXIMUM RATINGS

Electronic and mechanical stress momentarily exceeded absolute maximum ratings may cause permanent damage and may degrade the lifetime and safety for both device and system using the device in the field. The functional operation at or over these absolute maximum ratings are not assured.

RECOMMENDED OPERATING CONDITIONS

Recommended Operating Conditions

Symbol	Item	Rating	Unit
V_{IN}	Input Voltage	3.5 to 36	V
Ta	Operating Temperature Range	−40 to 125	°C

RECOMMENDED OPERATING CONDITIONS

All of electronic equipment should be designed that the mounted semiconductor devices operate within the recommended operating conditions. The semiconductor devices cannot operate normally over the recommended operating conditions, even if they are used over such conditions by momentary electronic noise or surge. And the semiconductor devices may receive serious damage when they continue to operate over the recommended operating conditions.

(1) Duration time: 200 ms
(2) Refer to *POWER DISSIPATION* for detailed information.

ELECTRICAL CHARACTERISTICS

C_{IN} = C_{OUT} = 0.1 µF, unless otherwise noted.

The specifications surrounded by ☐ are guaranteed by design engineering at -40°C ≤ Ta ≤ 125°C.

R1524x (-AE) Electrical Characteristics (Ta = 25°C)

Symbol	Item	Conditions		Min.	Typ.	Max.	Unit
I_{SS}	Supply Current	V_{IN} = 14 V, I_{OUT} = 0 mA	V_{SET} ≤ 5.0 V		2.2	6.5	µA
			5.0 V < V_{SET}		2.5	6.8	
Istandby	Standby Current	V_{IN} = 36 V, V_{CE} = 0 V			0.1	1.0	µA
V_{OUT}	Output Voltage	V_{SET} + 1 V[1] ≤ V_{IN} ≤ 36 V, I_{OUT} = 1 mA	Ta = 25°C	×0.994		×1.006	V
			−40°C ≤ Ta ≤ 125°C	×0.984		×1.016	
ΔV_{OUT} /ΔI_{OUT}	Load Regulation	V_{IN} = V_{SET} + 3.0 V, 1 mA ≤ I_{OUT} ≤ 200 mA		Refer to the *Product-specific Electrical Characteristics*			
ΔV_{OUT} /ΔV_{IN}	Line Regulation	V_{SET} + 1 V[1] ≤ V_{IN} ≤ 36 V, I_{OUT} = 1 mA	V_{SET} < 3.3 V	-20	5	20	mV
			3.3 V ≤ V_{SET}	-0.02	0.01	0.02	%/V
V_{DIF}	Dropout Voltage	I_{OUT} = 200 mA		Refer to the *Product-specific Electrical Characteristics*			
I_{LIM}	Output Current Limit	V_{IN} = V_{SET} + 3.0 V		220	350	420	mA
I_{SC}	Short Current Limit	V_{IN} = 3.5 V, V_{OUT} = 0 V		60	80	110	mA
V_{CEH}	CE Pin Input Voltage, high	V_{IN} = VSET + 1 V[1]		2.0		36	V
V_{CEL}	CE Pin Input Voltage, low	V_{IN} = 36 V		0		1.0	V
I_{PD}	CE Pull-down Current	V_{IN} = 36 V, V_{CE} = 2 V			0.2	0.6	µA
T_{TSD}	Thermal Shutdown Detection Temperature	Junction Temperature			160		°C
T_{TSR}	Thermal Shutdown Released Temperature	Junction Temperature			135		°C

All test items listed under Electrical Characteristics are done under the pulse load condition (Tj ≈ Ta = 25°C).

[1] V_{SET} ≤ 2.5 V, V_{IN} = 3.5 V

The specifications surrounded by ☐ are guaranteed by design engineering at -40°C ≤ Ta ≤ 125°C.

R1524x (-AE) Product-specific Electrical Characteristics (Ta = 25°C)

Product Name	V_{OUT} (V) (Ta = 25°C)			V_{OUT} (V) (−40°C ≤ Ta ≤ 125°C)			$\Delta V_{OUT}/\Delta I_{OUT}$ (mV)			V_{DIF} (V)	
	MIN.	TYP.	MAX.	MIN.	TYP.	MAX.	MIN.	TYP.	MAX.	TYP.	MAX.
R1524x018x	1.7892	1.80	1.8108	1.7712	1.80	1.8288				1.6	2.5
R1524x025x	2.4850	2.50	2.5150	2.4600	2.50	2.5400					
R1524x028x	2.7832	2.80	2.8168	2.7552	2.80	2.8448				1.2	2.2
R1524x030x	2.9820	3.00	3.0180	2.9520	3.00	3.0480	-10	10	40		
R1524x033x	3.2802	3.30	3.3198	3.2472	3.30	3.3528					
R1524x034x	3.3796	3.40	3.4204	3.3456	3.40	3.4544				0.8	2.0
R1524x050x	4.9700	5.00	5.0300	4.9200	5.00	5.0800					
R1524x055x	5.4670	5.50	5.5330	5.4120	5.50	5.5880					
R1524x060x	5.9640	6.00	6.0360	5.9040	6.00	6.0960					
R1524x064x	6.3616	6.40	6.4384	6.2976	6.40	6.5024				0.6	
R1524x070x	6.9580	7.00	7.0420	6.8880	7.00	7.1120					
R1524x075x	7.4550	7.50	7.5450	7.3800	7.50	7.6200					
R1524x080x	7.9520	8.00	8.0480	7.8720	8.00	8.1280					1.2
R1524x085x	8.4490	8.50	8.5510	8.3640	8.50	8.6360	-18	18	72		
R1524x090x	8.9460	9.00	9.0540	8.8560	9.00	9.1440					
R1524x100x	9.9400	10.0	10.0600	9.8400	10.0	10.1600				0.5	
R1524x105x	10.4370	10.5	10.5630	10.3320	10.5	10.6680					
R1524x110x	10.9340	11.0	11.0660	10.8240	11.0	11.1760					
R1524x120x	11.9280	12.0	12.0720	11.8080	12.0	12.1920					

C_{IN} = C_{OUT} = 0.1 µF, unless otherwise noted.

R1524x (-KE) Electrical Characteristics (−40°C ≤ Ta ≤ 125°C)

Symbol	Item	Conditions		Min.	Typ.	Max.	Unit
I_{SS}	Supply Current	V_{IN} = 14 V I_{OUT} = 0 mA	V_{SET} ≤ 5.0 V		2.2	6.5	µA
			5.0 V < V_{SET}		2.5	6.8	
Istandby	Standby Current	V_{IN} = 36 V, V_{CE} = 0 V			0.1	1.0	µA
V_{OUT}	Output Voltage	V_{SET} + 1 V[(1)] ≤ V_{IN} ≤ 36 V, I_{OUT} = 1 mA	Ta = 25°C	×0.994		×1.006	V
			−40°C ≤ Ta ≤ 125°C	×0.984		×1.016	
ΔV_{OUT} /ΔI_{OUT}	Load Regulation	V_{IN} = V_{SET} + 3.0 V 1 mA ≤ I_{OUT} ≤ 200 mA		Refer to the *Product-specific Electrical Characteristics*			
ΔV_{OUT} /ΔV_{IN}	Line Regulation	V_{SET} + 1 V[(1)] ≤ V_{IN} ≤ 36 V, I_{OUT} = 1 mA	V_{SET} < 3.3 V	-20	5	20	mV
			3.3 V ≤ V_{SET}	-0.02	0.01	0.02	%/V
V_{DIF}	Dropout Voltage	I_{OUT} = 200 mA		Refer to the *Product-specific Electrical Characteristics*			
I_{LIM}	Output Current Limit	V_{IN} = V_{SET} + 3.0 V		220	350	420	mA
I_{SC}	Short Current Limit	V_{IN} = 3.5 V, V_{OUT} = 0 V		60	80	110	mA
V_{CEH}	CE Pin Input Voltage, high	V_{IN} = VSET + 1 V[(1)]		2.0		36	V
V_{CEL}	CE Pin Input Voltage, low	V_{IN} = 36 V		0		1.0	V
I_{PD}	CE Pull-down Current	V_{IN} = 36 V, V_{CE} = 2 V			0.2	0.6	µA
T_{TSD}	Thermal Shutdown Detection Temparature	Junction Temperature		150	160		°C
T_{TSR}	Thermal Shutdown Released Temperature	Junction Temperature		125	135		°C

[(1)] V_{SET} ≤ 2.5 V, V_{IN} = 3.5 V

R1524x (-KE) Product-specific Electrical Characteristics (−40°C ≤ Ta ≤ 125°C)

Product Name	V_{OUT} (V) (Ta = 25°C)			V_{OUT} (V) (−40°C ≤ Ta ≤ 125°C)			$\Delta V_{OUT}/\Delta I_{OUT}$ (mV)			V_{DIF} (V)	
	MIN.	TYP.	MAX.	MIN.	TYP.	MAX.	MIN.	TYP.	MAX.	TYP.	MAX.
R1524x018x	1.7892	1.80	1.8108	1.7712	1.80	1.8288	-10	10	40	1.6	2.5
R1524x025x	2.4850	2.50	2.5150	2.4600	2.50	2.5400				1.2	2.2
R1524x028x	2.7832	2.80	2.8168	2.7552	2.80	2.8448					
R1524x030x	2.9820	3.00	3.0180	2.9520	3.00	3.0480					
R1524x033x	3.2802	3.30	3.3198	3.2472	3.30	3.3528				0.8	2.0
R1524x034x	3.3796	3.40	3.4204	3.3456	3.40	3.4544					
R1524x050x	4.9700	5.00	5.0300	4.9200	5.00	5.0800				0.6	1.2
R1524x055x	5.4670	5.50	5.5330	5.4120	5.50	5.5880	-18	18	72		
R1524x060x	5.9640	6.00	6.0360	5.9040	6.00	6.0960					
R1524x064x	6.3616	6.40	6.4384	6.2976	6.40	6.5024					
R1524x070x	6.9580	7.00	7.0420	6.8880	7.00	7.1120					
R1524x075x	7.4550	7.50	7.5450	7.3800	7.50	7.6200					
R1524x080x	7.9520	8.00	8.0480	7.8720	8.00	8.1280				0.5	
R1524x085x	8.4490	8.50	8.5510	8.3640	8.50	8.6360					
R1524x090x	8.9460	9.00	9.0540	8.8560	9.00	9.1440					
R1524x100x	9.9400	10.0	10.0600	9.8400	10.0	10.1600					
R1524x105x	10.4370	10.5	10.5630	10.3320	10.5	10.6680					
R1524x110x	10.9340	11.0	11.0660	10.8240	11.0	11.1760					
R1524x120x	11.9280	12.0	12.0720	11.8080	12.0	12.1920					


THEORY OF OPERATION

Thermal Shutdown

R1524x has a built-in thermal shutdown circuit, which stops the regulator operation if the junction temperature of this device increases to 160°C (Typ.) or higher. If the temperature drops to 135°C (Typ.) or lower, the regulator restarts the operation. Unless eliminating the overheating problem, the regulator turns on and off repeatedly and as a result, a pulse shaped output voltage is generated.

APPLICATION INFORMATION


TYPICAL APPLICATIONS



C1 = Ceramic 0.1 µF
C2 = Ceramic 0.1 µF

R1524x Typical Applications

TYPICAL APPLICATION FOR IC CHIP BREAKDOWN PREVENTION



C1 = Ceramic 0.1 µF
C2 = Ceramic 0.1 µF

R1524x Typical Application for IC Chip Breakdown Prevention

When a sudden surge of electrical current travels along the V_{OUT} pin and GND due to a short-circuit, electrical resonance of a circuit involving an output capacitor (C2) and a short circuit inductor generates a negative voltage and may damage the device or the load devices. Connecting a schottky diode (D1) between the V_{OUT} pin and GND has the effect of preventing damage to them.

TECHNICAL NOTES

Phase Compensation

In the R1524x, phase compensation is provided to secure stable operation even when the load current is varied. For this purpose, make sure to use 0.1 µF or more of a capacitor (C2).

In case of using a tantalum type capacitor and the ESR (Equivalent Series Resistance) value of the capacitor is large, the output might be unstable. Evaluate the circuit including consideration of frequency characteristics.

Connect 0.1 µF or more of a capacitor (C1) between V_{DD} and GND, and as close as possible to the pins.

PCB Layout

For SOT-23-5 package type, wire the following GND pins together: No. 1 and No. 2

For SOT-89-5 package type, wire the following GND pins together: No. 2 and No. 4.


For HSOP-6J package type, wire the following GND pins together: No. 2, No. 4, and No. 5.

TYPICAL CHARACTERISTICS


Note: Typical Characteristics are intended to be used as reference data; they are not guaranteed.

1) Output Voltage vs. Output Current (Ta = 25°C)


R1524x018B




R1524x033B




R1524x050B



R1524x090B




R1524x120B




2) Output Voltage vs. Input Voltage (Ta = 25°C)


R1524x018B




R1524x033B




R1524x050B



R1524x090B




R1524x120B




3) Supply Current vs. Temperature


R1524x018B




R1524x033B




R1524x050B



R1524x090B




R1524x120B




4) Supply Current vs. Input Voltage


R1524x018B



R1524x033B




R1524x120B




5) Output Voltage vs. Temperature (I_{OUT} = 1mA)


R1524x018B




R1524x033B




R1524x050B



R1524x090B




R1524x120B




6) Dropout Voltage vs. Output Current


R1524x018B




R1524x033B




R1524x050B




R1524x090B



R1524x120B




7) Dropout Voltage vs. Output Voltage (Ta = 25°C)




8) Ripple Rejection vs. Input Voltage (Ta = 25°C, Ripple = 0.2Vpp, I_{out} = 50mA)


R1524x018B (C_2 = 0.1µF)




R1524x018B (C_2 = 10µF)




R1524x033B (C_2 = 0.1µF)




R1524x033B (C_2 = 10µF)




R1524x050B (C_2 = 0.1µF)




R1524x050B (C_2 = 10µF)




R1524x090B (C_2 = 0.1µF)




R1524x090B (C_2 = 10µF)



R1524x120B (C_2 = 0.1µF)




R1524x120B (C_2 = 10µF)




9) Ripple Rejection vs. Frequency (Ta = 25°C, Ripple = 0.2Vpp)


R1524x018B (C_2 = 0.1µF)




R1524x018B (C_2 = 10µF)




R1524x033B (C_2 = 0.1µF)




R1524x033B (C_2 = 10µF)




R1524x050B (C_2 = 0.1µF)




R1524x050B (C_2 = 10µF)




R1524x090B (C_2 = 0.1µF)




R1524x090B (C_2 = 10µF)



R1524x120B (C_2 = 0.1µF)




R1524x120B (C_2 = 10µF)




10) Input Transient Response (Ta = 25°C)


R1524x018B




R1524x033B




R1524x050B



R1524x090B




R1524x120B




11) Load Transient Response (Ta = 25°C)


R1524x018B




R1524x033B




R1524x050B



R1524x090B





R1524x120B




12) CE Transient Response (Ta = 25°C)


R1524x018B







R1524x033B







R1524x050B







R1524x090B






R1524x120B






13) Power-on Transient Response (Ta = 25°C, V_{CE} = 5 V)

R1524x018B





R1524x033B




R1524x050B

R1524x090B






R1524x120B




14) Load Dump (Ta = 25°C)


R1524x018B




R1524x033B




R1524x050B



R1524x090B




R1524x120B




15) Cranking (Ta = 25°C)


R1524x050B



R1524x090B



R1524x120B




Input Transient/Load Transient vs. Output Capacity (C2)

R1524 performs a stable operation by using 0.1 µF of ceramic capacitor as the output capacitor. However, the variation of output voltage may not meet the demand of the system when input voltage and load current vary. In such cases, the variation of output voltage can be minimized significantly by using 10 µF or higher ceramic capacitor. When using an electrolytic capacitor for the output line, place the electrolytic capacitor outer side of the ceramic capacitor arranged close to the IC.


Input Transient Response

R1524x033B




Load Transient Response

R1524x033B




ESR vs. Output Current


It is recommended that a ceramic type capacitor be used for this device. However, other types of capacitors having lower ESR can also be used. The relation between the output current (I_{OUT}) and the ESR of output capacitor is shown below.




R1524x018B




R1524x033B




R1524x050B



R1524x090B



R1524x120B



Measurement Conditions

Frequency Band: 10 Hz to 2 MHz

Measurement Temperature: −40°C to 125°C

Hatched area: Noise level is 40 μV (average) or below

Ceramic Capacitors:
C_{IN} = 0.1 μF, Murata, GRM188R71H104JA93D
C_{OUT} = 0.1 μF, TDK, CGA3E2X7R1E104K

Ver. A

The power dissipation of the package is dependent on PCB material, layout, and environmental conditions. The following measurement conditions are based on JEDEC STD. 51-7.

Measurement Conditions


Item	Measurement Conditions
Environment	Mounting on Board (Wind Velocity = 0 m/s)
Board Material	Glass Cloth Epoxy Plastic (Four-Layer Board)
Board Dimensions	76.2 mm × 114.3 mm × 0.8 mm
Copper Ratio	Outer Layer (First Layer): Less than 95% of 50 mm Square Inner Layers (Second and Third Layers): Approx. 100% of 50 mm Square Outer Layer (Fourth Layer): Approx. 100% of 50 mm Square
Through-holes	ϕ 0.3 mm × 7 pcs

Measurement Result (Ta = 25°C, Tjmax = 150°C)


Item	Measurement Result
Power Dissipation	830 mW
Thermal Resistance (θja)	θja = 150°C/W
Thermal Characterization Parameter (ψjt)	ψjt = 51°C/W

θja: Junction-to-Ambient Thermal Resistance


ψjt: Junction-to-Top Thermal Characterization Parameter



Power Dissipation vs. Ambient Temperature




Measurement Board Pattern



SOT-23-5 Package Dimensions

①②③: Product Code ⋯ Refer to *Part Marking List*

④⑤: Lot Number ⋯ Alphanumeric Serial Number



SOT-23-5 Part Markings

NOTICE
There can be variation in the marking when different AOI (Automated Optical Inspection) equipment is used. In the case of recognizing the marking characteristic with AOI, please contact our sales or our distributor before attempting to use AOI.

R1524NxxxB Part Marking List

Product Name	①	②	③	V_{SET}
R1524N018B	C	T	7	1.8 V
R1524N025B	C	T	8	2.5 V
R1524N028B	C	T	9	2.8 V
R1524N030B	C	S	0	3.0 V
R1524N033B	C	T	0	3.3 V
R1524N034B	C	T	1	3.4 V
R1524N050B	C	T	2	5.0 V
R1524N055B	C	S	1	5.5 V
R1524N060B	C	T	3	6.0 V
R1524N064B	C	S	2	6.4 V
R1524N070B	C	S	5	7.0 V
R1524N075B	C	S	4	7.5 V
R1524N080B	C	T	4	8.0 V
R1524N085B	C	T	5	8.5 V
R1524N090B	C	T	6	9.0 V
R1524N100B	C	S	6	10.0 V
R1524N105B	C	S	7	10.5 V
R1524N110B	C	S	8	11.0 V
R1524N120B	C	S	9	12.0 V

Ver. A

The power dissipation of the package is dependent on PCB material, layout, and environmental conditions. The following measurement conditions are based on JEDEC STD. 51-7.

Measurement Conditions


Item	Measurement Conditions
Environment	Mounting on Board (Wind Velocity = 0 m/s)
Board Material	Glass Cloth Epoxy Plastic (Four-Layer Board)
Board Dimensions	76.2 mm × 114.3 mm × 0.8 mm
Copper Ratio	Outer Layer (First Layer): Less than 95% of 50 mm Square Inner Layers (Second and Third Layers): Approx. 100% of 50 mm Square Outer Layer (Fourth Layer): Approx. 100% of 50 mm Square
Through-holes	ϕ 0.3 mm × 13 pcs

Measurement Result (Ta = 25°C, Tjmax = 150°C)


Item	Measurement Result
Power Dissipation	3200 mW
Thermal Resistance (θja)	θja = 38°C/W
Thermal Characterization Parameter (ψjt)	ψjt = 13°C/W

θja: Junction-to-Ambient Thermal Resistance


ψjt: Junction-to-Top Thermal Characterization Parameter



Power Dissipation vs. Ambient Temperature




Measurement Board Pattern



SOT-89-5 Package Dimensions

①②③④: Product Code ⋯ Refer to *Part Marking List*

⑤⑥: Lot Number ⋯ Alphanumeric Serial Number



SOT-89-5 Part Markings

NOTICE
There can be variation in the marking when different AOI (Automated Optical Inspection) equipment is used. In the case of recognizing the marking characteristic with AOI, please contact our sales or our distributor before attempting to use AOI.

R1524HxxxB Part Marking List

Product Name	① ② ③	V_{SET}
R1524H018B	J 1 8 B	1.8 V
R1524H025B	J 2 5 B	2.5 V
R1524H028B	J 2 8 B	2.8 V
R1524H030B	J 3 0 B	3.0 V
R1524H033B	J 3 3 B	3.3 V
R1524H034B	J 3 4 B	3.4 V
R1524H050B	J 5 0 B	5.0 V
R1524H055B	J 5 5 B	5.5 V
R1524H060B	J 6 0 B	6.0 V
R1524H064B	J 6 4 B	6.4 V
R1524H070B	J 7 0 B	7.0 V
R1524H075B	J 7 5 B	7.5 V
R1524H080B	J 8 0 B	8.0 V
R1524H085B	J 8 5 B	8.5 V
R1524H090B	J 9 0 B	9.0 V
R1524H100B	J A 0 B	10.0 V
R1524H105B	J A 5 B	10.5 V
R1524H110B	J B 0 B	11.0 V
R1524H120B	J C 0 B	12.0 V

Ver. A

The power dissipation of the package is dependent on PCB material, layout, and environmental conditions. The following measurement conditions are based on JEDEC STD. 51-7.

Measurement Conditions


Item	Measurement Conditions
Environment	Mounting on Board (Wind Velocity = 0 m/s)
Board Material	Glass Cloth Epoxy Plastic (Four-Layer Board)
Board Dimensions	76.2 mm × 114.3 mm × 0.8 mm
Copper Ratio	Outer Layer (First Layer): Less than 95% of 50 mm Square Inner Layers (Second and Third Layers): Approx. 100% of 50 mm Square Outer Layer (Fourth Layer): Approx. 100% of 50 mm Square
Through-holes	ϕ 0.3 mm × 28 pcs

Measurement Result (Ta = 25°C, Tjmax = 150°C)


Item	Measurement Result
Power Dissipation	3400 mW
Thermal Resistance (θja)	θja = 37°C/W
Thermal Characterization Parameter (ψjt)	ψjt = 7°C/W

θja: Junction-to-Ambient Thermal Resistance


ψjt: Junction-to-Top Thermal Characterization Parameter



Power Dissipation vs. Ambient Temperature




Measurement Board Pattern



HSOP-6J Package Dimensions

①②③④: Product Code ⋯ Refer to *Part Marking List*

⑤⑥: Lot Number ⋯ Alphanumeric Serial Number



HSOP-6J Part Markings

NOTICE
There can be variation in the marking when different AOI (Automated Optical Inspection) equipment is used. In the case of recognizing the marking characteristic with AOI, please contact our sales or our distributor before attempting to use AOI.

R1524SxxxB Part Marking List

Product Name	①	②	③	④	V_{SET}
R1524S018B	A	1	8	B	1.8 V
R1524S025B	A	2	5	B	2.5 V
R1524S028B	A	2	8	B	2.8 V
R1524S030B	A	3	0	B	3.0 V
R1524S033B	A	3	3	B	3.3 V
R1524S034B	A	3	4	B	3.4 V
R1524S050B	A	5	0	B	5.0 V
R1524S055B	A	5	5	B	5.5 V
R1524S060B	A	6	0	B	6.0 V
R1524S064B	A	6	4	B	6.4 V
R1524S070B	A	7	0	B	7.0 V
R1524S075B	A	7	5	B	7.5 V
R1524S080B	A	8	0	B	8.0 V
R1524S085B	A	8	5	B	8.5 V
R1524S090B	A	9	0	B	9.0 V
R1524S100B	A	A	0	B	10.0 V
R1524S105B	A	A	5	B	10.5 V
R1524S110B	A	B	0	B	11.0 V
R1524S120B	A	C	0	B	12.0 V

Ver. B

The power dissipation of the package is dependent on PCB material, layout, and environmental conditions. The following measurement conditions are based on JEDEC STD. 51-7.

Measurement Conditions


Item	Measurement Conditions
Environment	Mounting on Board (Wind Velocity = 0 m/s)
Board Material	Glass Cloth Epoxy Plastic (Four-Layer Board)
Board Dimensions	76.2 mm × 114.3 mm × 0.8 mm
Copper Ratio	Outer Layer (First Layer): Less than 95% of 50 mm Square Inner Layers (Second and Third Layers): Approx. 100% of 50 mm Square Outer Layer (Fourth Layer): Approx. 100% of 50 mm Square
Through-holes	ϕ 0.3 mm × 21 pcs

Measurement Result (Ta = 25°C, Tjmax = 150°C)


Item	Measurement Result
Power Dissipation	3600 mW
Thermal Resistance (θja)	θja = 34.5°C/W
Thermal Characterization Parameter (ψjt)	ψjt = 10°C/W

θja: Junction-to-Ambient Thermal Resistance


ψjt: Junction-to-Top Thermal Characterization Parameter



Power Dissipation vs. Ambient Temperature



Measurement Board Pattern




HSOP-8E Package Dimensions

∗ The tab on the bottom of the package shown by blue circle is substrate potential (GND). It is recommended that this tab be connected to the ground plane on the board but it is possible to leave the tab floating.

①②③④⑤⑥: Product Code ⋯ Refer to *Part Marking List*

⑦⑧⑨: Lot Number ⋯ Alphanumeric Serial Number



HSOP-8E Part Markings

NOTICE
There can be variation in the marking when different AOI (Automated Optical Inspection) equipment is used. In the case of recognizing the marking characteristic with AOI, please contact our sales or our distributor before attempting to use AOI.

R1524SxxxH Part Marking List

Product Name	① ② ③ ④ ⑤ ⑥	V_{SET}
R1524S018H	R S 0 1 7 A	1.8 V
R1524S025H	R S 0 1 7 B	2.5 V
R1524S028H	R S 0 1 7 C	2.8 V
R1524S030H	R S 0 1 7 D	3.0 V
R1524S033H	R S 0 1 7 E	3.3 V
R1524S034H	R S 0 1 7 F	3.4 V
R1524S050H	R S 0 1 7 H	5.0 V
R1524S055H	R S 0 1 7 J	5.5 V
R1524S060H	R S 0 1 7 K	6.0 V
R1524S064H	R S 0 1 7 L	6.4 V
R1524S070H	R S 0 1 7 S	7.0 V
R1524S075H	R S 0 1 7 R	7.5 V
R1524S080H	R S 0 1 7 M	8.0 V
R1524S085H	R S 0 1 7 N	8.5 V
R1524S090H	R S 0 1 7 P	9.0 V
R1524S100H	R S 0 1 7 T	10.0 V
R1524S105H	R S 0 1 7 U	10.5 V
R1524S110H	R S 0 1 7 V	11.0 V
R1524S120H	R S 0 1 7 W	12.0 V

1. The products and the product specifications described in this document are subject to change or discontinuation of production without notice for reasons such as improvement. Therefore, before deciding to use the products, please refer to our sales representatives for the latest information thereon.
2. The materials in this document may not be copied or otherwise reproduced in whole or in part without the prior written consent of us.
3. This product and any technical information relating thereto are subject to complementary export controls (so-called KNOW controls) under the Foreign Exchange and Foreign Trade Law, and related politics ministerial ordinance of the law. (Note that the complementary export controls are inapplicable to any application-specific products, except rockets and pilotless aircraft, that are insusceptible to design or program changes.) Accordingly, when exporting or carrying abroad this product, follow the Foreign Exchange and Foreign Trade Control Law and its related regulations with respect to the complementary export controls.
4. The technical information described in this document shows typical characteristics and example application circuits for the products. The release of such information is not to be construed as a warranty of or a grant of license under our or any third party's intellectual property rights or any other rights.
5. The products listed in this document are intended and designed for automotive applications. Those customers intending to use a product in an application requiring extreme quality and reliability, for example, in a highly specific application where the failure or misoperation of the product could result in human injury or death should first contact us.
    - Aerospace Equipment
    - Equipment Used in the Deep Sea
    - Power Generator Control Equipment (nuclear, steam, hydraulic, etc.)
    - Life Maintenance Medical Equipment
    - Fire Alarms / Intruder Detectors
    - Vehicle Control Equipment (airplane, railroad, ship, etc.)
    - Various Safety Devices
    - Traffic control system
    - Combustion equipment

    In case your company desires to use this product for any applications other than general electronic equipment mentioned above, make sure to contact our company in advance. Note that the important requirements mentioned in this section are not applicable to cases where operation requirements such as application conditions are confirmed by our company in writing after consultation with your company.
6. We are making our continuous effort to improve the quality and reliability of our products, but semiconductor products are likely to fail with certain probability. In order to prevent any injury to persons or damages to property resulting from such failure, customers should be careful enough to incorporate safety measures in their design, such as redundancy feature, fire containment feature and fail-safe feature. We do not assume any liability or responsibility for any loss or damage arising from misuse or inappropriate use of the products.
7. The products have been designed and tested to function within controlled environmental conditions. Do not use products under conditions that deviate from methods or applications specified in this datasheet. Failure to employ the products in the proper applications can lead to deterioration, destruction or failure of the products. We shall not be responsible for any bodily injury, fires or accident, property damage or any consequential damages resulting from misuse or misapplication of the products.
8. Quality Warranty

    8-1. Quality Warranty Period

    In the case of a product purchased through an authorized distributor or directly from us, the warranty period for this product shall be one (1) year after delivery to your company. For defective products that occurred during this period, we will take the quality warranty measures described in section 8-2. However, if there is an agreement on the warranty period in the basic transaction agreement, quality assurance agreement, delivery specifications, etc., it shall be followed.

    8-2. Quality Warranty Remedies

    When it has been proved defective due to manufacturing factors as a result of defect analysis by us, we will either deliver a substitute for the defective product or refund the purchase price of the defective product.
    Note that such delivery or refund is sole and exclusive remedies to your company for the defective product.

    8-3. Remedies after Quality Warranty Period

    With respect to any defect of this product found after the quality warranty period, the defect will be analyzed by us. On the basis of the defect analysis results, the scope and amounts of damage shall be determined by mutual agreement of both parties. Then we will deal with upper limit in Section 8-2. This provision is not intended to limit any legal rights of your company.
9. Anti-radiation design is not implemented in the products described in this document.
10. The X-ray exposure can influence functions and characteristics of the products. Confirm the product functions and characteristics in the evaluation stage.
11. WLCSP products should be used in light shielded environments. The light exposure can influence functions and characteristics of the products under operation or storage.
12. Warning for handling Gallium and Arsenic (GaAs) products (Applying to GaAs MMIC, Photo Reflector). These products use Gallium (Ga) and Arsenic (As) which are specified as poisonous chemicals by law. For the prevention of a hazard, do not burn, destroy, or process chemically to make them as gas or power. When the product is disposed of, please follow the related regulation and do not mix this with general industrial waste or household waste.
13. Please contact our sales representatives should you have any questions or comments concerning the products or the technical information.

NISSHINBO

Nisshinbo Micro Devices Inc.

Official website
https://www.nisshinbo-microdevices.co.jp/en/

Purchase information
https://www.nisshinbo-microdevices.co.jp/en/buy/