# LDO Regulator for RF and Analog Circuits - Ultra-Low Noise and High PSRR

## 250 mA

# NCP160

The NCP160 is a linear regulator capable of supplying 250 mA output current. Designed to meet the requirements of RF and analog circuits, the NCP160 device provides low noise, high PSRR, low quiescent current, and very good load/line transients. The device is designed to work with a 1 μF input and a 1 μF output ceramic capacitor. It is available in two thickness ultra−small 0.35P, 0.64 mm x 0.64 mm Chip Scale Package (CSP) and XDFN−4 0.65P, 1 mm x 1 mm.

### Features

- Operating Input Voltage Range: 1.9 V to 5.5 V
- Available in Fixed Voltage Option: 1.8 V to 5.14 V
- ±2% Accuracy Over Load/Temperature
- Ultra Low Quiescent Current Typ. 18 μA
- Standby Current: Typ. 0.1 μA
- Very Low Dropout: 80 mV at 250 mA
- Ultra High PSRR: Typ. 98 dB at 20 mA, f = 1 kHz
- Ultra Low Noise: 10 $\mu V_{RMS}$
- Stable with a 1 μF Small Case Size Ceramic Capacitors
- Available in −WLCSP4 0.64 mm x 0.64 mm x 0.4 mm
  −WLCSP4 0.64 mm x 0.64 mm x 0.33 mm
  −XDFN4 1 mm x 1 mm x 0.4 mm
- These Devices are Pb−Free and are RoHS Compliant

### Typical Applications

- Battery−powered Equipment
- Wireless LAN Devices
- Smartphones, Tablets
- Cameras, DVRs, STB and Camcorders



WLCSP4
CASE 567JZ




WLCSP4
CASE 567KA





XDFN4
CASE 711AJ

### MARKING DIAGRAMS





X or XX = Specific Device Code
M = Date Code

### PIN CONNECTIONS




(Top View)




(Top View)

### ORDERING INFORMATION

See detailed ordering, marking and shipping information on page 17 of this data sheet.

NOTE: Some of the devices on this data sheet have been **DISCONTINUED**. Please refer to the table on page 18.

© Semiconductor Components Industries, LLC, 2017





**Figure 1. Typical Application Schematics**





**Figure 2. Simplified Schematic Block Diagram**

## PIN FUNCTION DESCRIPTION

| Pin No. CSP4 | Pin No. XDFN4 | Pin Name | Description |
|---|---|---|---|
| A1 | 4 | IN | Input voltage supply pin |
| A2 | 1 | OUT | Regulated output voltage. The output should be bypassed with small 1 μF ceramic capacitor. |
| B1 | 3 | EN | Chip enable: Applying $V_{EN}$ < 0.4 V disables the regulator, Pulling $V_{EN}$ > 1.2 V enables the LDO. |
| B2 | 2 | GND | Common ground connection |
| – | EPAD | EPAD | Expose pad can be tied to ground plane for better power dissipation |



Share Feedback
Your Opinion Matters

## ABSOLUTE MAXIMUM RATINGS

| Rating | Symbol | Value | Unit |
|---|---|---|---|
| Input Voltage (Note 1) | $V_{IN}$ | −0.3 V to 6 | V |
| Output Voltage | $V_{OUT}$ | −0.3 to $V_{IN}$ + 0.3, max. 6 | V |
| Chip Enable Input | $V_{CE}$ | −0.3 V to 6 | V |
| Output Short Circuit Duration | $t_{SC}$ | unlimited | s |
| Maximum Junction Temperature | $T_J$ | 150 | °C |
| Storage Temperature | $T_{STG}$ | −55 to 150 | °C |
| ESD Capability, Human Body Model (Note 2) | $ESD_{HBM}$ | 2000 | V |
| ESD Capability, Machine Model (Note 2) | $ESD_{MM}$ | 200 | V |

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

1. Refer to ELECTRICAL CHARACTERISTICS and APPLICATION INFORMATION for Safe Operating Area.
2. This device series incorporates ESD protection and is tested by the following methods:
   ESD Human Body Model tested per EIA/JESD22−A114
   ESD Machine Model tested per EIA/JESD22−A115
   Latchup Current Maximum Rating tested per JEDEC standard: JESD78.

## THERMAL CHARACTERISTICS

| Rating | Symbol | Value | Unit |
|---|---|---|---|
| Thermal Characteristics, CSP4 (Note 3)<br>Thermal Resistance, Junction−to−Air | $R_{\theta JA}$ | 108 | °C/W |
| Thermal Characteristics, XDFN4 (Note 3)<br>Thermal Resistance, Junction−to−Air | | 198.1 | |

3. Measured according to JEDEC board specification. Detailed description of the board can be found in JESD51−7



Share Feedback
Your Opinion Matters

**ELECTRICAL CHARACTERISTICS** $-40°C \le T_J \le 125°C$; $V_{IN} = V_{OUT(NOM)} + 1$ V; $I_{OUT} = 1$ mA, $C_{IN} = C_{OUT} = 1$ μF, unless otherwise noted. $V_{EN} = 1.2$ V. Typical values are at $T_J = +25°C$ (Note 4).

| Parameter | Test Conditions | | Symbol | Min | Typ | Max | Unit |
|---|---|---|---|---|---|---|---|
| Operating Input Voltage | | | $V_{IN}$ | 1.9 | | 5.5 | V |
| Output Voltage Accuracy | $V_{IN} = V_{OUT(NOM)} + 1$ V<br>0 mA ≤ $I_{OUT}$ ≤ 250 mA | | $V_{OUT}$ | −2 | | +2 | % |
| Line Regulation | $V_{OUT(NOM)} + 1$ V ≤ $V_{IN}$ ≤ 5.5 V | | $Line_{Reg}$ | | 0.02 | | %/V |
| Load Regulation | $I_{OUT}$ = 1 mA to 250 mA | | $Load_{Reg}$ | | 0.001 | | %/mA |
| Dropout Voltage (Note 5) | $I_{OUT}$ = 250 mA | $V_{OUT(NOM)}$ = 1.8 V | $V_{DO}$ | | 180 | 250 | mV |
| | | $V_{OUT(NOM)}$ = 2.5 V | | | 110 | 175 | |
| | | $V_{OUT(NOM)}$ = 2.8 V | | | 95 | 160 | |
| | | $V_{OUT(NOM)}$ = 2.85 V | | | 95 | 160 | |
| | | $V_{OUT(NOM)}$ = 3.0 V | | | 90 | 155 | |
| | | $V_{OUT(NOM)}$ = 3.2 V | | | 85 | 149 | |
| | | $V_{OUT(NOM)}$ = 3.3 V | | | 80 | 145 | |
| | | $V_{OUT(NOM)}$ = 3.5 V | | | 75 | 140 | |
| | | $V_{OUT(NOM)}$ = 4.5 V | | | 65 | 120 | |
| | | $V_{OUT(NOM)}$ = 5.0 V | | | 75 | 105 | |
| | | $V_{OUT(NOM)}$ = 5.14 V | | | 60 | 105 | |
| Output Current Limit | $V_{OUT}$ = 90% $V_{OUT(NOM)}$ | | $I_{CL}$ | 250 | 700 | | mA |
| Short Circuit Current | $V_{OUT}$ = 0 V | | $I_{SC}$ | | 690 | | |
| Quiescent Current | $I_{OUT}$ = 0 mA | | $I_Q$ | | 18 | 23 | μA |
| Shutdown Current | $V_{EN} \le 0.4$ V, $V_{IN}$ = 4.8 V | | $I_{DIS}$ | | 0.01 | 1 | μA |
| EN Pin Threshold Voltage | EN Input Voltage “H” | | $V_{ENH}$ | 1.2 | | | V |
| | EN Input Voltage “L” | | $V_{ENL}$ | | | 0.4 | |
| EN Pull Down Current | $V_{EN}$ = 4.8 V | | $I_{EN}$ | | 0.2 | 0.5 | μA |
| Turn−On Time | $C_{OUT}$ = 1 μF, From assertion of $V_{EN}$ to $V_{OUT}$ = 95% $V_{OUT(NOM)}$ | | | | 120 | | μs |
| Power Supply Rejection Ratio | $I_{OUT}$ = 20 mA | f = 100 Hz<br>f = 1 kHz<br>f = 10 kHz<br>f = 100 kHz | PSRR | | 91<br>98<br>82<br>48 | | dB |
| Output Voltage Noise | f = 10 Hz to 100 kHz | $I_{OUT}$ = 1 mA<br>$I_{OUT}$ = 250 mA | $V_N$ | | 14<br>10 | | $\mu V_{RMS}$ |
| Thermal Shutdown Threshold | Temperature rising | | $T_{SDH}$ | | 160 | | °C |
| | Temperature falling | | $T_{SDL}$ | | 140 | | °C |
| Active Output Discharge Resistance | $V_{EN}$ < 0.4 V, Version A only | | $R_{DIS}$ | | 280 | | Ω |
| Line Transient (Note 6) | $V_{IN}$ = ($V_{OUT(NOM)}$ + 1 V) to ($V_{OUT(NOM)}$ + 1.6 V) in 30 μs, $I_{OUT}$ = 1 mA | | $Tran_{LINE}$ | −1 | | | mV |
| | $V_{IN}$ = ($V_{OUT(NOM)}$ + 1.6 V) to ($V_{OUT(NOM)}$ + 1 V) in 30 μs, $I_{OUT}$ = 1 mA | | | | | +1 | |
| Load Transient (Note 6) | $I_{OUT}$ = 1 mA to 200 mA in 10 μs | | $Tran_{LOAD}$ | −40 | | | mV |
| | $I_{OUT}$ = 200 mA to 1mA in 10 μs | | | | | +40 | |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

4. Performance guaranteed over the indicated operating temperature range by design and/or characterization. Production tested at $T_A = 25°C$. Low duty cycle pulse techniques are used during the testing to maintain the junction temperature as close to ambient as possible.
5. Dropout voltage is characterized when $V_{OUT}$ falls 100 mV below $V_{OUT(NOM)}$.
6. Guaranteed by design.



Share Feedback
Your Opinion Matters

## TYPICAL CHARACTERISTICS





**Figure 3. Output Voltage vs. Temperature – $V_{OUT}$ = 1.8 V – XDFN Package**





**Figure 4. Output Voltage vs. Temperature – $V_{OUT}$ = 2.5 V – XDFN Package**





**Figure 5. Output Voltage vs. Temperature – $V_{OUT}$ = 3.3 V – XDFN Package**





**Figure 6. Output Voltage vs. Temperature – $V_{OUT}$ = 3.3 V – CSP Package**





**Figure 7. Output Voltage vs. Temperature – $V_{OUT}$ = 5.14 V – XDFN Package**





**Figure 8. Line Regulation vs. Temperature – $V_{OUT}$ = 1.8 V**



Share Feedback
Your Opinion Matters

## TYPICAL CHARACTERISTICS





**Figure 9. Line Regulation vs. Temperature – $V_{OUT}$ = 3.3 V**





**Figure 10. Line Regulation vs. Temperature – $V_{OUT}$ = 5.14 V**





**Figure 11. Load Regulation vs. Temperature – $V_{OUT}$ = 1.8 V**





**Figure 12. Load Regulation vs. Temperature – $V_{OUT}$ = 3.3 V**





**Figure 13. Load Regulation vs. Temperature – $V_{OUT}$ = 5.14 V**





**Figure 14. Ground Current vs. Load Current – $V_{OUT}$ = 1.8 V**



Share Feedback
Your Opinion Matters

## TYPICAL CHARACTERISTICS





**Figure 15. Ground Current vs. Load Current – $V_{OUT}$ = 3.3 V**





**Figure 16. Ground Current vs. Load Current – $V_{OUT}$ = 5.14 V**





**Figure 17. Dropout Voltage vs. Load Current – $V_{OUT}$ = 1.8 V**





**Figure 18. Dropout Voltage vs. Load Current – $V_{OUT}$ = 3.3 V**





**Figure 19. Dropout Voltage vs. Load Current – $V_{OUT}$ = 5.14 V**





**Figure 20. Dropout Voltage vs. Temperature– $V_{OUT}$ = 1.8 V**



Share Feedback
Your Opinion Matters

## TYPICAL CHARACTERISTICS





**Figure 21. Comparison Dropout for XDFN and CSP – 1.8 V**





**Figure 22. Comparison Dropout for XDFN and CSP – 3.3 V**





**Figure 23. Comparison Dropout for XDFN and CSP – 5.14 V**



Share Feedback
Your Opinion Matters

## TYPICAL CHARACTERISTICS





**Figure 24. Dropout Voltage vs. Temperature– $V_{OUT}$ = 3.3 V**





**Figure 25. Dropout Voltage vs. Temperature– $V_{OUT}$ = 5.14 V**





**Figure 26. Current Limit vs. Temperature**





**Figure 27. Short Circuit Current vs. Temperature**





**Figure 28. Enable Threshold Voltage vs. Temperature**





**Figure 29. Enable Current Temperature**



Share Feedback
Your Opinion Matters

## TYPICAL CHARACTERISTICS





**Figure 30. Disable Current vs. Temperature**







**Figure 31. Discharge Resistivity vs. Temperature**




| $I_{OUT}$ | RMS Output Noise (μV) | |
|---|---|---|
| | 10 Hz – 100 kHz | 100 Hz – 100 kHz |
| 1 mA | 14.62 | 14.10 |
| 10 mA | 11.12 | 10.48 |
| 250 mA | 10.37 | 9.82 |

**Figure 32. Output Voltage Noise Spectral Density – $V_{OUT}$ = 1.8 V**




| $I_{OUT}$ | RMS Output Noise (μV) | |
|---|---|---|
| | 10 Hz – 100 kHz | 100 Hz – 100 kHz |
| 1 mA | 16.9 | 15.79 |
| 10 mA | 12.64 | 11.13 |
| 250 mA | 11.96 | 10.64 |

**Figure 33. Output Voltage Noise Spectral Density – $V_{OUT}$ = 3.3 V**



Share Feedback
Your Opinion Matters

## TYPICAL CHARACTERISTICS





**Figure 34. Power Supply Rejection Ratio, $V_{OUT}$ = 1.8 V**





**Figure 35. Power Supply Rejection Ratio, $V_{OUT}$ = 3.3 V**





**Figure 36. Power Supply Rejection Ratio, $V_{OUT}$ = 5.14 V**





**Figure 37. Stability vs. ESR**





**Figure 38. Enable Turn−on Response − $C_{OUT}$ = 1 μF, $I_{OUT}$ = 10 mA**





**Figure 39. Enable Turn−on Response − $C_{OUT}$ = 1 μF, $I_{OUT}$ = 250 mA**



Share Feedback
Your Opinion Matters

## TYPICAL CHARACTERISTICS





**Figure 40. Line Transient Response – $V_{OUT}$ = 1.8 V**





**Figure 41. Line Transient Response – $V_{OUT}$ = 3.3 V**





**Figure 42. Line Transient Response – $V_{OUT}$ = 5.14 V**





**Figure 43. Turn−on/off – Slow Rising $V_{IN}$**





**Figure 44. Load Transient Response – 1 mA to 250 mA – $V_{OUT}$ = 1.8 V**





**Figure 45. Load Transient Response – 250 mA to 1 mA – $V_{OUT}$ = 1.8 V**



Share Feedback
Your Opinion Matters

## TYPICAL CHARACTERISTICS





**Figure 46. Load Transient Response – 1 mA to 250 mA – $V_{OUT}$ = 3.3 V**





**Figure 47. Load Transient Response – 250 mA to 1 mA – $V_{OUT}$ = 3.3 V**





**Figure 48. Load Transient Response – 1 mA to 250 mA – $V_{OUT}$ = 5.14 V**





**Figure 49. Load Transient Response – 250 mA to 1 mA – $V_{OUT}$ = 5.14 V**





**Figure 50. Short Circuit and Thermal Shutdown**





**Figure 51. Enable Turn−off**



Share Feedback
Your Opinion Matters

## APPLICATIONS INFORMATION

### General

The NCP160 is an ultra−low noise 250 mA low dropout regulator designed to meet the requirements of RF applications and high performance analog circuits. The NCP160 device provides very high PSRR and excellent dynamic response. In connection with low quiescent current this device is well suitable for battery powered application such as cell phones, tablets and other. The NCP160 is fully protected in case of current overload, output short circuit and overheating.

### Input Capacitor Selection ($C_{IN}$)

Input capacitor connected as close as possible is necessary for ensure device stability. The X7R or X5R capacitor should be used for reliable performance over temperature range. The value of the input capacitor should be 1 μF or greater to ensure the best dynamic performance. This capacitor will provide a low impedance path for unwanted AC signals or noise modulated onto constant input voltage. There is no requirement for the ESR of the input capacitor but it is recommended to use ceramic capacitors for their low ESR and ESL. A good input capacitor will limit the influence of input trace inductance and source resistance during sudden load current changes.

### Output Decoupling ($C_{OUT}$)

The NCP160 requires an output capacitor connected as close as possible to the output pin of the regulator. The recommended capacitor value is 1 μF and X7R or X5R dielectric due to its low capacitance variations over the specified temperature range. The NCP160 is designed to remain stable with minimum effective capacitance of 0.7 μF to account for changes with temperature, DC bias and package size. Especially for small package size capacitors such as 0201 the effective capacitance drops rapidly with the applied DC bias. Please refer Figure 52.





**Figure 52. Capacity vs DC Bias Voltage**

There is no requirement for the minimum value of Equivalent Series Resistance (ESR) for the $C_{OUT}$ but the maximum value of ESR should be less than 2 Ω. Larger output capacitors and lower ESR could improve the load transient response or high frequency PSRR. It is not recommended to use tantalum capacitors on the output due to their large ESR. The equivalent series resistance of tantalum capacitors is also strongly dependent on the temperature, increasing at low temperature.

### Enable Operation

The NCP160 uses the EN pin to enable/disable its device and to deactivate/activate the active discharge function.

If the EN pin voltage is <0.4 V the device is guaranteed to be disabled. The pass transistor is turned−off so that there is virtually no current flow between the IN and OUT. The active discharge transistor is active so that the output voltage $V_{OUT}$ is pulled to GND through a 280 Ω resistor. In the disable state the device consumes as low as typ. 10 nA from the $V_{IN}$.

If the EN pin voltage >1.2 V the device is guaranteed to be enabled. The NCP160 regulates the output voltage and the active discharge transistor is turned−off.

The EN pin has internal pull−down current source with typ. value of 200 nA which assures that the device is turned−off when the EN pin is not connected. In the case where the EN function isn't required the EN should be tied directly to IN.

### Output Current Limit

Output Current is internally limited within the IC to a typical 700 mA. The NCP60 will source this amount of current measured with a voltage drops on the 90% of the nominal $V_{OUT}$. If the Output Voltage is directly shorted to ground ($V_{OUT}$ = 0 V), the short circuit protection will limit the output current to 690 mA (typ). The current limit and short circuit protection will work properly over whole temperature range and also input voltage range. There is no limitation for the short circuit duration.

### Thermal Shutdown

When the die temperature exceeds the Thermal Shutdown threshold ($T_{SD}$ − 160°C typical), Thermal Shutdown event is detected and the device is disabled. The IC will remain in this state until the die temperature decreases below the Thermal Shutdown Reset threshold ($T_{SDU}$ − 140°C typical). Once the IC temperature falls below the 140°C the LDO is enabled again. The thermal shutdown feature provides the protection from a catastrophic device failure due to accidental overheating. This protection is not intended to be used as a substitute for proper heat sinking.

### Power Dissipation

As power dissipated in the NCP160 increases, it might become necessary to provide some thermal relief. The maximum power dissipation supported by the device is dependent upon board design and layout. Mounting pad configuration on the PCB, the board material, and the ambient temperature affect the rate of junction temperature rise for the part.


Share Feedback
Your Opinion Matters

The maximum power dissipation the NCP160 can handle is given by:

$$P_{D(MAX)} = \frac{[125°C - T_A]}{\theta_{JA}} \quad \text{(eq. 1)}$$

The power dissipated by the NCP160 for given application conditions can be calculated from the following equations:

$$P_D \approx V_{IN} \cdot I_{GND} + I_{OUT}(V_{IN} - V_{OUT}) \quad \text{(eq. 2)}$$





**Figure 53. $\theta_{JA}$ and $P_{D\ (MAX)}$ vs. Copper Area (CSP4)**





**Figure 54. $\theta_{JA}$ and $P_{D\ (MAX)}$ vs. Copper Area (XDFN4)**



Share Feedback
Your Opinion Matters

### Reverse Current

The PMOS pass transistor has an inherent body diode which will be forward biased in the case that $V_{OUT} > V_{IN}$. Due to this fact in cases, where the extended reverse current condition can be anticipated the device may require additional external protection.

### Power Supply Rejection Ratio

The NCP160 features very high Power Supply Rejection ratio. If desired the PSRR at higher frequencies in the range 100 kHz – 10 MHz can be tuned by the selection of $C_{OUT}$ capacitor and proper PCB layout.

### Turn−On Time

The turn−on time is defined as the time period from EN assertion to the point in which $V_{OUT}$ will reach 98% of its nominal value. This time is dependent on various application conditions such as $V_{OUT(NOM)}$, $C_{OUT}$, $T_A$.

### PCB Layout Recommendations

To obtain good transient performance and good regulation characteristics place $C_{IN}$ and $C_{OUT}$ capacitors close to the device pins and make the PCB traces wide. In order to minimize the solution size, use 0402 or 0201 capacitors with appropriate capacity. Larger copper area connected to the pins will also improve the device thermal resistance. The actual power dissipation can be calculated from the equation above (Equation 2). Expose pad can be tied to the GND pin for improvement power dissipation and lower device temperature.



Share Feedback
Your Opinion Matters

## ORDERING INFORMATION

| Device | Nominal Output Voltage | Description | Marking | Rotation | Package | Shipping† |
|---|---|---|---|---|---|---|
| NCP160AFCS180T2G | 1.8 V | 250 mA, Active Discharge | A | 0° | WLCSP4 CASE 567KA (Pb-Free) | 5000 / Tape & Reel |
| NCP160AFCS270T2G | 2.7 V | | 4 | 0° | | |
| NCP160AFCS280T2G | 2.8 V | | E | 0° | | |
| NCP160AFCSC280T2G | 2.8 V | 250 mA, Active Discharge, Backside Coating | E | 0° | | |
| NCP160AFCS285T2G | 2.85 V | 250 mA, Active Discharge | F | 0° | | |
| NCP160AFCS300T2G | 3.0 V | | J | 0° | | |
| NCP160AFCS330T2G | 3.3 V | | K | 0° | | |
| NCP160AFCS350T2G | 3.5 V | | L | 0° | | |
| NCP160AFCS500T2G | 5.0 V | | R | 0° | | |
| NCP160AFCS514T2G | 5.14 V | | Q | 0° | | |
| NCP160BFCS250T2G | 2.5 V | 250 mA, Non-Active Discharge | D | 90° | | |
| NCP160BFCS350T2G | 3.5 V | | L | 90° | | |
| NCP160BFCS450T2G | 4.5 V | | P | 90° | | |
| NCP160AFCT180T2G | 1.8 V | 250 mA, Active Discharge | A | 0° | WLCSP4 CASE 567JZ (Pb-Free) | 5000 or 10000 / Tape & Reel (Note 7) |
| NCP160AFCT280T2G | 2.8 V | | E | 0° | | |
| NCP160AFCT285T2G | 2.85 V | | F | 0° | | |
| NCP160AFCT300T2G | 3.0 V | | J | 0° | | |
| NCP160AFCT330T2G | 3.3 V | | K | 0° | | |
| NCP160AFCTC330T2G | 3.3 V | 250 mA, Active Discharge, Backside Coating | K | 0° | | |
| NCP160AFCT450T2G | 4.5 V | 250 mA, Active Discharge | P | 0° | | |
| NCP160AFCT500T2G | 5.0 V | | R | 0° | | |
| NCP160AFCT514T2G | 5.14 V | | Q | 0° | | |
| NCP160AFCTC180T2G | 1.8 V | 250 mA, Active Discharge, Backside Coating | A | 0° | | |
| NCP160BFCT210T2G | 2.1 V | 250 mA, Non-Active Discharge | T | 90° | | |
| NCP160BFCT280T2G | 2.8 V | | E | 90° | | |
| NCP160BFCT350T2G | 3.5 V | | L | 90° | | |
| NCP160BFCT450T2G | 4.5 V | | P | 90° | | |
| NCP160BFCT514T2G | 5.14 V | | Q | 90° | | |
| NCP160AMX180TBG | 1.8 V | 250 mA, Active Discharge | DF | | XDFN4 (Pb-Free) | 3000 or 5000 / Tape & Reel (Note 8) |
| NCP160AMX1825TBG | 1.825 V | | D7 | | | |
| NCP160AMX280TBG | 2.8 V | | DH | | | |
| NCP160AMX290TBG | 2.9 V | | D4 | | | |
| NCP160AMX300TBG | 3.0 V | | DK | | | |
| NCP160AMX320TBG | 3.2 V | | DY | | | |
| NCP160AMX330TBG | 3.3 V | | DA | | | |
| NCP160AMX350TBG | 3.5 V | | DL | | | |
| NCP160AMX500TBG | 5.0 V | | DW | | | |
| NCP160BMX280TBG | 2.8 V | 250 mA, Non-Active Discharge | EH | | | |
| NCP160BMX285TBG | 2.85 V | | EJ | | | |
| NCP160BMX514TBG | 5.14 V | | EC | | | |



Share Feedback
Your Opinion Matters

**DISCONTINUED** (Note 9)

**ORDERING INFORMATION** (continued)


| Device | Nominal Output Voltage | Description | Marking | Rotation | Package | Shipping† |
|---|---|---|---|---|---|---|
| NCP160AFCS250T2G | 2.5 V | 250 mA, Active Discharge | D | 0° | WLCSP4 CASE 567KA (Pb-Free) | 5000 / Tape & Reel |
| NCP160AFCS2925T2G | 2.925 V | | T | 0° | | |
| NCP160AFCS320T2G | 3.2 V | | V | 0° | | |
| NCP160AFCS370T2G | 3.7 V | | Y | 0° | | |
| NCP160AFCS450T2G | 4.5 V | | P | 0° | | |
| NCP160BFCS180T2G | 1.8 V | 250 mA, Non-Active Discharge | A | 90° | | |
| NCP160BFCS280T2G | 2.8 V | | E | 90° | | |
| NCP160BFCS285T2G | 2.85 V | | F | 90° | | |
| NCP160BFCS2925T2G | 2.925 V | | T | 90° | | |
| NCP160BFCS300T2G | 3.0 V | | J | 90° | | |
| NCP160BFCS330T2G | 3.3 V | | K | 90° | | |
| NCP160BFCS500T2G | 5.0 V | | R | 90° | | |
| NCP160BFCS514T2G | 5.14 V | | Q | 90° | | |
| NCP160AFCT250T2G | 2.5 V | 250 mA, Active Discharge | D | 0° | WLCSP4 CASE 567JZ (Pb-Free) | 5000 or 10000 / Tape & Reel (Note 7) |
| NCP160AFCT350T2G | 3.5 V | | L | 0° | | |
| NCP160BFCT180T2G | 1.8 V | 250 mA, Non-Active Discharge | A | 90° | | |
| NCP160BFCT250T2G | 2.5 V | | D | 90° | | |
| NCP160BFCT285T2G | 2.85 V | | F | 90° | | |
| NCP160BFCT300T2G | 3.0 V | | J | 90° | | |
| NCP160BFCT330T2G | 3.3 V | | K | 90° | | |
| NCP160BFCT500T2G | 5.0 V | | R | 90° | | |
| NCP160AMX250TBG | 2.5 V | 250 mA, Active Discharge | DG | | XDFN4 (Pb-Free) | 3000 or 5000 / Tape & Reel (Note 8) |
| NCP160AMX275TBG | 2.75 V | | D2 | | | |
| NCP160AMX285TBG | 2.85 V | | DJ | | | |
| NCP160AMX310TBG | 3.1 V | | D3 | | | |
| NCP160AMX450TBG | 4.5 V | | DM | | | |
| NCP160AMX514TBG (Note 8) | 5.14 V | | DC | | | |
| NCP160BMX180TBG | 1.8 V | 250 mA, Non-Active Discharge | EF | | | |
| NCP160BMX1825TBG (Note 8) | 1.825 V | | E7 | | | |
| NCP160BMX250TBG | 2.5 V | | EG | | | |
| NCP160BMX275TBG (Note 8) | 2.75 V | | E2 | | | |
| NCP160BMX300TBG | 3.0 V | | EK | | | |
| NCP160BMX330TBG | 3.3 V | | EA | | | |
| NCP160BMX350TBG | 3.5 V | | EL | | | |
| NCP160BMX450TBG | 4.5 V | | EM | | | |
| NCP160BMX500TBG | 5.0 V | | EW | | | |

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

7. Product processed after April 1, 2023 are shipped with quantity 10000 units / tape & reel.
8. Product processed after October 1, 2022 are shipped with quantity 5000 units / tape & reel.
9. **DISCONTINUED:** These devices are not recommended for new design. Please contact your **onsemi** representative for information. The most current information on these devices may be available on www.onsemi.com.





Share Feedback
Your Opinion Matters




**WLCSP4, 0.64x0.64x0.33**
CASE 567JZ
ISSUE B

DATE 16 MAY 2022








NOTES:

1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 2009.
2. CONTROLLING DIMENSION: MILLIMETERS
3. DATUM C, THE SEATING PLANE, IS DEFINED BY THE SPERICAL CROWNS OF THE SOLDER BUMPS.
4. COPLANARITY APPLIES TO THE SPHERICAL CROWNS OF THE SOLDER BUMPS.
5. DIMENSION b IS MEASURED AT THE MAXIMUM SOLDER BALL DIAMETER PARALLEL TO DATUM C.

| DIM | MILLIMETERS | | |
|---|---|---|---|
| | MIN. | NOM. | MAX. |
| A | --- | --- | 0.33 |
| A1 | 0.04 | 0.06 | 0.08 |
| A2 | 0.23 REF | | |
| b | 0.180 | 0.200 | 0.220 |
| D | 0.610 | 0.640 | 0.670 |
| E | 0.610 | 0.640 | 0.670 |
| e | 0.35 BSC | | |




RECOMMENDED
MOUNTING FOOTPRINT *
(NSMD PAD TYPE)

* For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

**GENERIC**
**MARKING DIAGRAM***




X = Specific Device Code
M = Date Code

*This information is generic. Please refer to device data sheet for actual part marking. Pb−Free indicator, “G” or microdot “▪”, may or may not be present. Some products may not follow the Generic Marking.

| | | |
|---|---|---|
| **DOCUMENT NUMBER:** | **98AON85781F** | Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped “CONTROLLED COPY” in red. |
| **DESCRIPTION:** | **WLCSP4, 0.64X0.64x0.33** | **PAGE 1 OF 1** |


**onsemi** and onsemi are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.


© Semiconductor Components Industries, LLC, 2014


**WLCSP4, 0.64x0.64**
CASE 567KA
ISSUE B

DATE 24 MAR 2020

**SCALE 4:1**








NOTES:

1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 2009.
2. CONTROLLING DIMENSION: MILLIMETERS
3. DATUM C, THE SEATING PLANE, IS DEFINED BY THE SPERICAL CROWNS OF THE CONTACT BALLS.
4. COPLANARITY APPLIES TO THE SPHERICAL CROWNS OF THE CONTACT BALLS.
5. DIMENSION b IS MEASURED AT THE MAXIMUM CONTACT BALL DIAMETER PARALLEL TO DATUM C.

| | MILLIMETERS | | |
|---|---|---|---|
| DIM | MIN. | NOM. | MAX. |
| A | 0.355 | 0.405 | 0.455 |
| A1 | 0.13 | 0.15 | 0.17 |
| A2 | 0.255 REF | | |
| b | 0.167 | 0.187 | 0.207 |
| D | 0.610 | 0.640 | 0.670 |
| E | 0.610 | 0.640 | 0.670 |
| e | 0.35 BSC | | |




RECOMMENDED
MOUNTING FOOTPRINT*
(NSMD PAD TYPE)

* For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

**GENERIC**
**MARKING DIAGRAM***




X = Specific Device Code
M = Date Code

*This information is generic. Please refer to device data sheet for actual part marking. Pb−Free indicator, “G” or microdot “▪”, may or may not be present. Some products may not follow the Generic Marking.

| | | |
|---|---|---|
| **DOCUMENT NUMBER:** | **98AON85783F** | Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped “CONTROLLED COPY” in red. |
| **DESCRIPTION:** | **WLCSP4, 0.64X0.64** | **PAGE 1 OF 1** |


**onsemi** and onsemi are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

© Semiconductor Components Industries, LLC, 2014




**XDFN4 1.0x1.0, 0.65P**
CASE 711AJ
ISSUE C


DATE 08 MAR 2022




TOP VIEW




SIDE VIEW





DETAIL A


NOTES:

1. DIMENSIONING AND TOLERANCING PER. ASME Y14.5M, 1994.
2. CONTROLLING DIMENSION: MILLIMETERS
3. DIMENSION b APPLIES TO THE PLATED TERMINALS AND IS MEASURED BETWEEN 0.15 AND 0.20 FROM THE TERMINAL TIPS.
4. COPLANARITY APPLIES TO THE EXPOSED PAD AS WELL AS THE TERMINALS.

| | MILLIMETERS | | |
|---|---|---|---|
| DIM | MIN | NOM | MAX |
| A | 0.33 | 0.38 | 0.43 |
| A1 | 0.00 | --- | 0.05 |
| A3 | | 0.10 REF | |
| b | 0.15 | 0.20 | 0.25 |
| b2 | 0.02 | 0.07 | 0.12 |
| D | 0.90 | 1.00 | 1.10 |
| D2 | 0.43 | 0.48 | 0.53 |
| E | 0.90 | 1.00 | 1.10 |
| e | | 0.65 BSC | |
| L | 0.20 | | 0.30 |
| L2 | 0.07 | | 0.17 |





BOTTOM VIEW




RECOMMENDED
MOUNTING FOOTPRINT

* FOR ADDITIONAL INFORMATION ON OUR Pb-FREE STRATEGY AND SOLDERING DETAILS, PLEASE DOWNLOAD THE ONSEMI SOLDERING AND MOUNTING TECHNIQUES REFERENCE MANUAL, SOLDERRM/D

**GENERIC**
**MARKING DIAGRAM***




XX = Specific Device Code
M = Date Code

*This information is generic. Please refer to device data sheet for actual part marking. Pb−Free indicator, “G” or microdot “▪”, may or may not be present. Some products may not follow the Generic Marking.

| | | | |
|---|---|---|---|
| **DOCUMENT NUMBER:** | **98AON67179E** | Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped “CONTROLLED COPY” in red. | |
| **DESCRIPTION:** | **XDFN4, 1.0X1.0, 0.65P** | | **PAGE 1 OF 1** |

**onsemi** and onsemi are trademarks of Semiconductor Components Industries, LLC dba **onsemi** or its subsidiaries in the United States and/or other countries. **onsemi** reserves the right to make changes without further notice to any products herein. **onsemi** makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.

© Semiconductor Components Industries, LLC, 2012

**onsemi**, , and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "**onsemi**" or its affiliates and/or subsidiaries in the United States and/or other countries. **onsemi** owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of **onsemi**'s product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent−Marking.pdf. **onsemi** reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as−is" and **onsemi** makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

## ADDITIONAL INFORMATION

**TECHNICAL PUBLICATIONS**:
**Technical Library:** www.onsemi.com/design/resources/technical−documentation
**onsemi Website:** www.onsemi.com

**ONLINE SUPPORT**: www.onsemi.com/support
**For additional information, please contact your local Sales Representative at** www.onsemi.com/support/sales