



COAXIAL TERMINATIONS

SMA

3 WATTS



Part Number	Power		Frequency range (GHz)	V.S.W.R. (MAX)						Imp. (Ω)	Type
	avg. (W)	peak (W)		DC-1	1-2	2-4	4-8	8-12.4	12.4-18		
R404894119	3	500	DC-1	1.10						50 $\pm$ 5%	M
R404600000	3	250	DC-8	1.05		1.10	1.15			50 $\pm$ 5%	M
R404605000	3	250	DC-18	1.12			1.18	1.25	1.34	50 $\pm$ 5%	M



Part Number	A inch (mm)	B inch (mm)	Weight (g)
R404894119	.84" (21.3)	.43" (11.0)	10
R404600000 R404605000	1.17" (30)	.51" (13.0)	19

6 to 12 WATTS MEDIUM POWER

Part Number	Power		Frequency range (GHz)	V.S.W.R. (MAX)					Imp. (Ω)	Type
	avg. (W)	peak (W)		DC-2	2-4	4-8	8-12.4	12.4-18		
R404513000	6	4000	DC-8	1.10	1.15	1.25			50 $\pm$ 5%	M
R404513500	6	4000	DC-8	1.10	1.15	1.25			50 $\pm$ 5%	F
R404518000	6	4000	DC-12.4	1.10		1.20	1.30		50 $\pm$ 5%	M
R404518500	6	4000	DC-12.4	1.10		1.20	1.30		50 $\pm$ 5%	F
R404523000	6	300	DC-18	1.15		1.20	1.25	1.30	50 $\pm$ 5%	M
R404523500	6	300	DC-18	1.15		1.20	1.25	1.30	50 $\pm$ 5%	F
R404563000	12	4000	DC-8	1.10	1.15	1.25			50 $\pm$ 5%	M
R404563500	12	4000	DC-8	1.10	1.15	1.25			50 $\pm$ 5%	F
R404568000	12	4000	DC-12.4	1.10		1.20	1.30		50 $\pm$ 5%	M
R404568500	12	4000	DC-12.4	1.10		1.20	1.30		50 $\pm$ 5%	F
R404573000	12	300	DC-18	1.15		1.20	1.25	1.30	50 $\pm$ 5%	M
R404573500	12	300	DC-18	1.15		1.20	1.25	1.30	50 $\pm$ 5%	F



Part Number	A inch (mm)	B inch (mm)	Weight (g)
R404513000	1.22" (31)	1.02 (26)	22
R404513500	1.08" (27.5)		
R404518000	1.22" (31)		
R404518500	1.08" (27.5)		
R404523000	1.85" (47)		
R404523500	1.80" (45.8)		45

Part Number	A inch (mm)	B inch (mm)	Weight (g)
R404563000	1.73" (44)	1.38" (35)	62
R404563500	1.59" (40.5)		
R404568000	1.73" (44)		
R404568500	1.59" (40.5)		
R404573000	2.05" (52.2)		
R404573500	2.00" (51)		75