

LM150-12A15 series is one of Mornsun's dual output non-isolation enclosed AC-DC switching power supply. It features universal AC input and at the same time accepts DC input voltage, cost-effective, high efficiency, high reliability and double or reinforced insulation. These converters offer excellent EMC performance and meet IEC/EN61000-4, IEC/UL/EN62368, GB4943 standards and they are not only specific used in the laser galvanometer industry, but also widely used in current sensors, motors and other fields.

Selection Guide								
Certification	Part No.*	Output Power (W)	Nominal Output Voltage and Current (Vo/Io)		Output Voltage Adjustable Range	Efficiency at	Max. Capacitive Load (µF)	
			(Vo1/lo1)	(Vo2/lo2)	(ADJ) Io1 (V)	230VAC (%) Typ.	(vo1/vo2)	
EN/BIS/BS	LM150-12A15	150	+15V/5A	-15V/5A	13.5V-16.5V	85	6000	
Note: *Use suffi	x "C" for terminal w	ith protective co	ver and suffix "(o" for conforme	l coating	1		

Input Specifications							
Item	Operating Conditions			Min.	Тур.	Max.	Unit
Innut Voltago Dango	AC input		165		264	VAC	
Input Voltage Range	DC input			180		370	VDC
Input Voltage Frequency						63	Hz
Input Current	230VAC	230VAC				2.5	•
Inrush Current	230VAC Cold start			60		A	
Leakage Current	240VAC			<0.75mA			
Hot Plug			Unavailable				

Output Specificatio	ns					
Item	Operating Conditions	Min.	Тур.	Max.	Unit	
	10% - 100% load (Balanced load)	Vo1		±1.0		
Output Voltage Accuracy		Vo2		±3.0		%
Line Degulation	10% - 100% load (Balanced load)	Vo1		±0.5		
Line Regulation		Vo2		±0.5		
Load Regulation	10% - 100% load (Balanced load)	Vo1		±1.0		
LOGG Keguidilon		Vo2		±3.0		
Ripple & Noise*	20MHz bandwidth (peak-to-peak value)	Vo1/Vo2		100		mV
Temperature Coefficient				±0.03		%/ ℃
Minimum Load				10		%

MORNSUN®

MORNSUN Guangzhou Science & Technology Co., Ltd.

2022.05.13-A/3 Page 1 of 4

Stand-by Power Consumption	230VAC			5.5	W		
Hold-up Time	230VAC		22		ms		
Short Circuit Protection	ort Circuit Protection Recovery time <5s after the short circuit disappear.			Hiccup, continuous, self-recover			
Over-current Protection		110%-180% lo, hiccup, self-recover					
Over-voltage Protection	Balanced load, Vo1	\leqslant 21.75VDC (Hiccup, self-recover)					
	Over-temperature Protection Activation	Lileauna		80	90	- °C	
Over-temperature Protection	Over-temperature Protection Deactivation	Hiccup	65]	

Note: *The "Tip and barrel method" is used for ripple and noise test, output parallel 47µF electrolytic capacitor and 0.1µF ceramic capacitor, please refer to enclosed Switching Power Supply Application Notes for specific information.

General Specifications

ltem		Operating Conditions		Min.	Typ.	Max.	Unit	
	Input - output		3000		-	VAC		
Isolation Test	Input - 🕀	Electric strength test for 1min., leakag	1500					
	Output - 🕀		500					
1	Input - output Environment temperature: 25±5°C			50			MΩ	
Insulation	Input - 🕀	Relative humidity: <95%RH, non-conc	50					
Resistance	Output - 🕀	Testing voltage: 500VDC		50				
Operating Temperature				-30		+70	°C	
Storage Temperature				-40		+85		
Operating Humidity				10		95	0/ DU	
Storage Humi	dity	Non-condensing		20		90	%RH	
Power Deratin	g	Operating temperature derating	+50 ℃ to +70℃	2.5			%/ ℃	
Safety Standard				IS13252 (Part1) safety approved & EN62368 BS EN 62368-1(Report) Design refer to IEC/UL62368-1, EN60335-1, EN61558-1, GB4943.1				
Safety Class				CLASS I				
MTBF		MIL-HDBK-217F@25°C	MIL-HDBK-217F@25°C		>300,000 h			

Mechanical Specifications					
Case Material	Metal (AL1100, SGCC)				
Dimensions	159.0 x 97.0 x 30.0 mm				
Weight	420g (Typ.)				
Cooling Method	Air cooling				

Е E	CISPR32/EN55032			
F		CD 100 D		
-	CISPR32/EN55032	CLASS B		
larmonic current	IEC/EN61000-3-2	CLASS A (≤80% Load)		
licker	IEC/EN61000-3-3			
SD	IEC/EN61000-4-2	Contact ±6KV/Air ±8KV	Perf. Criteria A	
S	IEC/EN61000-4-3	10V/m	perf. Criteria A	
FT	IEC/EN61000-4-4	±4KV	perf. Criteria A	
urge	IEC/EN61000-4-5	line to line ± 2 KV/line to ground ± 4 KV	perf. Criteria A	
S	IEC/EN61000-4-6	10 Vr.m.s	perf. Criteria A	
oltage dips, short interruptions and voltage variations immunity	IEC/EN61000-4-11	0%, 70%	perf. Criteria B	
lic SI SI SI SI SI SI SI	cker D T rge ; Itage dips, short interruptions id voltage variations immunity	ckerIEC/EN61000-3-3DIEC/EN61000-4-2IEC/EN61000-4-3IEC/EN61000-4-3TIEC/EN61000-4-4rgeIEC/EN61000-4-5isIEC/EN61000-4-6Itage dips, short interruptions id voltage variations immunityIEC/EN61000-4-11	IEC/EN61000-3-3 D IEC/EN61000-4-2 Contact ±6KV/Air ±8KV IEC/EN61000-4-3 10V/m IEC/EN61000-4-4 ±4KV IEC/EN61000-4-5 line to line ±2KV/line to ground ±4KV IEC/EN61000-4-6 10 Vr.m.s Itage dips, short interruptions IEC/EN61000-4-11 0% 70%	

Notes: 1.*The power supply is considerated a component as part of system, all EMC items are tested on a metal plate (L x W x H, 360mm x 360mm x 1mm). Power supply should be combined with final equipment for EMC confirmation;



MORNSUN Guangzhou Science & Technology Co., Ltd.

2022.05.13-A/3 Page 2 of 4

Product Characteristic Curve









MORNSUN Guangzhou Science & Technology Co., Ltd.

2022.05.13-A/3 Page 3 of 4

Dimensions and Recommended Layout



	THIRD A	NGLE PROJE		\square
Right View			T	
000		Pin-	-Out]
000		Pin	Function	
-30.00 [1.181]-		1	AC(L)	
-30.00 [1.181]-	-	2	AC(N)	
	8	3		
		4	Vo2	
	3	5	COM	
	8	6	COM	
	3	-		1

Note:

Unit: mm[inch] ADJ: Output adjustable resistor Wire range: 22–12AWG Tightening torque: M4, Max 1.2N.m General tolerances: ±1.00[±0.039]

7

Vo1

Note:

- 1. For additional information on Product Packaging please refer to <u>www.mornsun-power.com</u>. Packaging bag number: 58220111 ;
- 2. Unless otherwise specified, parameters in this datasheet were measured under the conditions of Ta=25°C, humidity<75%RH with nominal input voltage and rated output load;
- 3. All index testing methods in this datasheet are based on our company corporate standards;
- 4. In order to improve the efficiency, there will be audible noise generated when work at light load, but it does not affect product performance and reliability;
- 5. We can provide product customization service, please contact our technicians directly for specific information;
- 6. Products are related to laws and regulations: see "Features" and "EMC";
- 7. The out case needs to be connected to PE () of system when the terminal equipment in operating;
- 8. CAUTION: Double pole, neutral fusing. Disconnect mains before servicing."/"ATTENTION: Double pôle/fusible sur le neutre. Débrancher lalimentation avant lentretien;
- 9. Our products shall be classified according to ISO14001 and related environmental laws and regulations, and shall be handled by qualified units;
- 10. The power supply is considered a component which will be installed into a terminal equipment. All EMC tests should be confirmed with the final equipment. Please consult our FAE for EMC test operation instructions.

Mornsun Guangzhou Science & Technology Co., Ltd.

Address: No. 5, Kehui St. 1, Kehui Development Center, Science Ave., Guangzhou Science City, Huangpu District, Guangzhou, P. R. ChinaTel: 86-20-38601850Fax: 86-20-38601272E-mail: info@mornsun.cnwww.mornsun-power.com

MORNSUN®

MORNSUN Guangzhou Science & Technology Co., Ltd.

2022.05.13-A/3 Page 4 of 4