

BNX029-01#

"#" indicates a package specification code.








< List of part numbers with package codes > BNX029-01K BNX029-01L BNX029-01B



Appearance & Shape







Features

BNX02 series is SMD type high performance and provides excellent noise suppression on DC power lines.

Features

- 1. Large rated current (10A-15A)
- 2. Supporting wide frequency range From 15kHz to 1GHz:35dB min. (BNX029)
- 3. Mounting area and volume is reduced.
- Effective for impulse noise such as electrostatic discharge or spike noise.

Applications

- 1. Displays (PDP/LCD-TV)
- 2. Digital AV equipment
- 3. Amusement equipment
- 4. PC peripheral equipment
- 5. Industry equipment, measurement equipment, power supplies



Other Usage

For general



Packaging Information

Packaging	Specifications	Minimum Order Quantity
K	330mm Embossed Tape	1500
L	180mm Embossed Tape	400
В	Bulk(Bag)	100

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2019/07/18



BNX029-01#

"#" indicates a package specification code.



Shape	SMD	
Length	12.1mm	
Length Tolerance	±0.2mm	
Width	9.1mm	
Width Tolerance	±0.2mm	
Thickness	3.5mm	
Thickness Tolerance	±0.2mm	
Rated Current	20A	
Operating Temperature Range	-40°C to 125°C	
Mass(typ.)	0.8g	
Rated Voltage	6.3Vdc	
Withstanding Voltage	15.8Vdc	
Insulation Resistance(min.)	0.5ΜΩ	
Insertion Loss	15kHz to 1GHz:35dB min. (Line impedance=50Ω)	

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/


Last updated :2019/07/18




BNX029-01#

"#" indicates a package specification code.








Insertion Loss Characteristics

In operating temperature exceeding +85°C, derating of current is necessary for BNX023/029 series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Equivalent Circuit

Derating of Rated Current

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



URL: https://www.murata.com/

Last updated :2019/07/18