

Please download the latest datasheet of BLM15BD221SZ1# from the official website of Murata Manufacturing

https://www.murata.com/en-global/products/productdetail?partno=BLM15BD221SZ1%23

BLM15BD221SZ1#

"#" indicates a package specification code.

Note: This datasheet may be out of date









< List of part numbers with package codes >

BLM15BD221SZ1J BLM15BD221SZ1B BLM15BD221SZ1D



Appearance & Shape













The chip ferrite beads BLM series is designed to work nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

BLM_B series can minimize attenuation of the signal waveform due to its sharp impedance characteristics. Various impedances are available to match signal frequency.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance.



Automotive
Usage

Infotainment



Packaging Information

Packaging	Specifications	Minimum Order Quantity
J	330mm Paper Tape	50000
В	Bulk(Bag)	1000
D	180mm Paper Tape	10000

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated : 2019/09/05



Note: This datasheet may be out of date $\underline{ Please \ download \ the \ latest \ data sheet \ of \ BLM15BD221SZ1\# \ from \ the \ of ficial \ website \ of \ Murata \ Manufacturing} }$

Co., Ltd. https://www.murata.com/en-global/products/productdetail?partno=BLM15BD221SZ1%23

BLM15BD221SZ1#

"#" indicates a package specification code.



Shape	SMD
Size Code (in mm)	1005
Size Code (in inch)	0402
Length	1.0mm
Length Tolerance	±0.05mm
Width	0.5mm
Width Tolerance	±0.05mm
Thickness	0.5mm
Thickness Tolerance	±0.05mm
Impedance (at 100MHz)	220Ω
Impedance (at 100MHz) Tolerance	±25%
Rated Current (at 85°C)	300mA
Rated Current (at 125°C)	300mA
DC Resistance(max.)	0.4Ω
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.001g
Number of Circuit	1

2 of 3

Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2019/09/05

^{1.} This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Note: This datasheet may be out of date.


 $\underline{ Please \ download \ the \ latest \ data sheet \ of \ BLM15BD221SZ1\# \ from \ the \ of ficial \ website \ of \ Murata \ Manufacturing} }$


Co., Ltd. https://www.murata.com/en-global/products/productdetail?partno=BLM15BD221SZ1%23

BLM15BD221SZ1#

"#" indicates a package specification code.







Impedance-Frequency Characteristics

Equivalent Circuit

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2019/09/05