### **Silicon Controlled Rectifier**

#### Features

- Available in JAN, JANTX, JANTXV per MIL-PRF-19500/276
- TO-5 & TO-39 (TO-205AD) Package
- Triggered Solid State Switches Used in Motors and Power Supplies
- Ideal for Sensing Circuit Applications and Control Systems



## Electrical Characteristics (T<sub>c</sub> = +25°C unless otherwise specified)

Parameter	Conditions		Symbol	Min.	Max.	Units
Subgroup 2 Testing			L L			I
	$R_2 = 1 k\Omega$ $R_2 = 2 k\Omega$	2N2323, S - 2N2329, S 2N2323A, AS - 2N2329A, AS	I <sub>RBX1</sub>	_	10	µA dc
Reverse Blocking Current		2N2323, S, A, AS 2N2324, S, A, AS 2N2326, S, A, AS 2N2328, S, A, AS 2N2328, S, A, AS 2N2329, S, A, AS				
	$R_2 = 1 k\Omega$ $R_2 = 2 k\Omega$	2N2323, S - 2N2329, S 2N2323A, AS - 2N2329A, AS	I <sub>FBX1</sub>	_	10	µA dc
Forward Blocking Current		2N2323, S, A, AS 2N2324, S, A, AS 2N2326, S, A, AS 2N2326, S, A, AS 2N2328, S, A, AS 2N2329, S, A, AS				
Reverse Gate Current (V <sub>KG</sub> = 6 Vdc)			I <sub>KG</sub>	—	200	µA dc
Gate Trigger Voltage & Current V <sub>2</sub> = V <sub>FBX</sub> = 6 Vdc; R <sub>L</sub> = 100 W	R <sub>e</sub> = 1 kΩ R <sub>e</sub> = 2 kΩ	2N2323, S - 2N2329, S 2N2323A, AS - 2N2329A, AS	V <sub>GT1</sub> I <sub>GT1</sub> V <sub>GT1</sub> I <sub>GT1</sub>	0.35  0.35	0.80 200 0.60 20	V dc µA dc V dc µA dc
Subgroup 4 Testing			1011		20	μπτασ
Exponential Rate of Voltage Rise $T_A = 125^{\circ}C$ 50 $\Omega \le R_L \le 400$ W, C = 0.1 to 1.0 µF, repetition rate = 60 pps, test duration = 15 seconds		2N2323, S - 2N2329, S 2N2323A, AS - 2N2329A, AS 2N2323, S, A, AS 2N2324, S, A, AS 2N2326, S, A, AS 2N2326, S, A, AS 2N2328, S, A, AS 2N2329, S, A, AS	V <sub>FBX</sub>	47 95 190 285 380	_	V dc
Forward "on" Voltage I <sub>FM</sub> = 4a (pk) (pulse), pulse width = 8.5 ms, max; duty cycle = 2% max.			$V_{FM}$	_	2.2	V (pk)
Holding Current						
$V_{AA} = 24 \text{ V dc max.}, I_F1 = 100 \text{ mA dc}, I_F2 = 10 \text{ mA dc}$ Gate trigger source voltage = 6 V dc, trigger pulse width = 25 µs min. $R_2 = 330 \Omega$	R <sub>3</sub> = 1 kΩ R <sub>3</sub> = 2 kΩ	2N2323, S - 2N2329, S 2N2323A, AS - 2N2329A, AS	I <sub>HOX</sub>	_	2.0	mA dc

VPT Components and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.vptcomponents.com</u> for additional data sheets and product information.





## **Silicon Controlled Rectifier**

Rev. V7

#### **Absolute Maximum Ratings**

Ratings	Symbol	2N2323, S/ 2N2323A, S	2N2324, S/ 2N2324A, S	2N2326, S/ 2N2326A, S	2N2328, S/ 2N2328A, S	2N2329, S/ 2N2329A, S	Unit
Reverse Voltage	V <sub>RM</sub>	50	100	200	300	400	V dc
Working Peak Reverse Voltage	V <sub>RM</sub>	75	150	300	400	500	V pk
Forward Blocking Voltage	V <sub>FBXM</sub>	50 <sup>3,4</sup>	100 <sup>3,4</sup>	200 <sup>3,4</sup>	300 <sup>3,4</sup>	400 <sup>3,4</sup>	V pk
Average Forward Current <sup>1</sup>	Ι <sub>ο</sub>	0.22					A dc
Forward Current Surge Peak <sup>2</sup>	I <sub>FSM</sub>	15					A dc
Cathode-Gate Current	V <sub>GKM</sub>	6					V pk
Operating Temperature	T <sub>OP</sub>	-65 to +150					°C
Storage Junction Temperature	T <sub>STG</sub>	-65 to +150					°C
Thermal Resistance, Junction to Ambient	R <sub>θJA</sub>	175					°C/W
Thermal Resistance, Junction to Case	$R_{\theta JC}$	15					°C/W

 This average forward current is for an ambient temperature of 80°C and 180 electrical degrees of conduction. For other operating conditions see figure 3 of MIL-PRF-19500/276.

 Surge current is non-recurrent. The rate of rise of peak surge current shall not exceed 40 A during the first 5 µs after switching from the "off" (blocking) to the "on" (conducting) state. This is measured from the point where the thyristor voltage has decayed to 90% of its initial blocking value.

3. Gate connected to cathode through 1,000 ohm resistor.

4. Gate connected to cathode through 2,000 ohm resistor.

2

### **Silicon Controlled Rectifier**



Rev. V7

### Outline Drawing (TO-5 & TO-39)

Symbol	Dimensions				Notes
	Inches		Millimeters		
	Min	Max	Min	Max	
CD	.305	.335	7.75	8.51	3
СН	.240	.260	6.10	6.60	
HD	.335	.370	8.51	9.40	3
LC	.200 TP		5.08 TP		4
LD	.016	.021	0.41	0.53	5, 6
LL					6, 7
LU	.016	.019	0.41	0.48	5, 6
L1		.050		1.27	5, 6
L2	.250		6.35		5, 6
Р	.100		2.54		
Q		.050		1.27	3
TL	.029	.045	0.74	1.14	8
TW	.028	.034	0.71	0.86	9
r		.010		0.25	10
α	45° TP		45° TP		4



NOTES:

- 1. Dimension are in inches. Millimeters are given for general information only.
- Terminal 1 = emitter, terminal 2 = base, terminal 3 = collector. The collector shall be internally connected to the case.
- 3. Body contour optional within zone defined by dimensions CD, HD, and Q.
- Leads at gauge plane .054 +.001 -.000 inch (1.37 +0.03 -0.00 mm) below seating plane shall be within .007 inch (0.18 mm) radius of true position (TP) at maximum material condition (MMC) relative to tab at MMC. The device may be measured by direct methods.
- Dimension LD applies between dimensions L2 and LL minimum. Diameter is uncontrolled in dimension L1 and beyond dimension LL minimum. Dimension LU applies between dimensions L1 and L2.
- All three leads.
- For non-"S" suffix devices (TO-205AA), dimension LL is 1.500 (38.10 mm) minimum, 1.750 (44.45 mm) maximum. For "S" suffix devices (TO-205AD), dimension LL is .500 (12.70 mm) minimum, .750 (19.05 mm) maximum.
- 8. Dimension TL measured from maximum HD.
- 9. Beyond r (radius) maximum, dimension TW shall be held for a minimum length of .011 inch (0.28 mm).
- 10. Dimension r (radius) applies to both inside corners of tab.
- In accordance with ASME Y14.5M, diameters are equivalent to \$\phi\$x symbology.

FIGURE 1. Physical dimensions for TO-205AA and TO-205AD packages (formerly TO-39, TO-5).

3

VPT Components and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.vptcomponents.com</u> for additional data sheets and product information.

### **Silicon Controlled Rectifier**



#### VPT COMPONENTS. ALL RIGHTS RESERVED.

Information in this document is provided in connection with VPT Components products. These materials are provided by VPT Components as a service to its customers and may be used for informational purposes only. Except as provided in VPT Components Terms and Conditions of Sale for such products or in any separate agreement related to this document, VPT Components assumes no liability whatsoever. VPT Components assumes no responsibility for errors or omissions in these materials. VPT Components may make changes to specifications and product descriptions at any time, without notice. VPT Components makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF VPT COMPONENTS PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PA-TENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. VPT COMPONENTS FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CON-TAINED WITHIN THESE MATERIALS. VPT COMPONENTS SHALL NOT BE LIABLE FOR ANY SPECIAL, IN-DIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVE-NUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

VPT Components products are not intended for use in medical, lifesaving or life sustaining applications. VPT Components customers using or selling VPT Components products for use in such applications do so at their own risk and agree to fully indemnify VPT Components for any damages resulting from such improper use or sale.

<sup>4</sup> 

VPT Components and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.vptcomponents.com</u> for additional data sheets and product information.